Silicon Photomultipliers for Gamma Radiation Detectors in Nuclear Medicine Applications

by

Rigoberto Chil Pérez

in partial fulfillment of the requirements for the degree of Doctor of
Philosophy in

Electrical Engineering, Electronics and Automation

Universidad Carlos III de Madrid

Advisor:

Juan José Vaquero López

September 2019

“Warning: If you are reading this then this warning is for you. Every word you read of this useless fine print is another second off your life. Don't you have other things to do? Is your life so empty that you honestly can't think of a better way to spend these moments? Or are you so impressed with authority that you give respect and credence to all that claim it? Do you read everything you're supposed to read? Do you think every thing you're supposed to think? Buy what you're told to want? Get out of your apartment. Meet a member of the opposite sex. Stop the excessive shopping and masturbation. Quit your job. Start a fight. Prove you're alive. If you don't claim your humanity you will become a statistic. You have been warned.”

— Chuck Palahniuk, *Fight Club*.

PUBLISHED AND SUBMITTED CONTENT

Journal Articles:

[1] Perez-Benito, D., **R. Chil**, J.M. Udias, M. Desco, and J.J. Vaquero. 2018. "SiPM-Based PET Detector Module for a 4π Span Scanner." *Nuclear Instruments and Methods in Physics Research Section A: Accelerators, Spectrometers, Detectors and Associated Equipment*, November. <https://doi.org/10.1016/J.NIMA.2018.10.179>.

(Author Contributions: Rigoberto Chil was responsible for designing and testing the case studies; David Pérez and Rigoberto Chil contributed equally. All authors were responsible for conceptualizing the framework, writing, editing & reviewing the paper.)

Conference Proceedings:

[2] **Chil, R.**, L. M. Fraile, J. Vaquero, E. Picado, A. Rodriguez-Moreno, M. C. Rodriguez-Sanchez, S. Borromeo, M. Desco, J. M. Udiás, and J. J. Vaquero. 2014. *Advanced Networked Modular Personal Dosimetry System. IFMBE Proceedings*. Vol. 41. Springer, Cham. https://doi.org/10.1007/978-3-319-00846-2_346.

(Author Contributions: Rigoberto Chil was responsible for designing and testing the case studies; All authors were responsible for conceptualizing the framework, writing, editing & reviewing the paper.)

[3] **Chil, R.**, G. Konstantinou, L.M. Fraile, J. Vaquero, C. Rodriguez, S. Borromeo, M. Desco, J.M. Udias, and J.J Vaquero. 2016. "Personal Dosimetry Geolocalized System for Radiation Monitoring." In *2016 IEEE Nuclear Science Symposium, Medical Imaging Conference and Room-Temperature Semiconductor Detector Workshop (NSS/MIC/RTSD)*, 1–2. IEEE. <https://doi.org/10.1109/NSSMIC.2016.8069698>.

(Author Contributions: Rigoberto Chil was responsible for designing and testing the case studies; All authors were responsible for conceptualizing the framework, writing, editing & reviewing the paper.)

[4] **Chil, R.**, G. Konstantinou, M. Desco, and J. J. Vaquero. 2015. "Highly Multiplexed DOI PET Detector Based on SiPM Sensors." In *2015 IEEE Nuclear Science Symposium and Medical Imaging Conference (NSS/MIC)*, 1–3. IEEE. <https://doi.org/10.1109/NSSMIC.2015.7582150>.

(Author Contributions: Rigoberto Chil was responsible for designing and testing the case studies; All authors were responsible for conceptualizing the framework, writing, editing & reviewing the paper.)

[5] **Chil, R.**, G. Konstantinou, M. Desco, and J.J Vaquero. 2016. "Compact, MR Compatible SiPM Small Animal PET DOI Detector." In *2016 IEEE Nuclear Science Symposium, Medical Imaging Conference and Room-Temperature Semiconductor Detector Workshop (NSS/MIC/RTSD)*, 1–2. IEEE. <https://doi.org/10.1109/NSSMIC.2016.8069413>.

(Author Contributions: Rigoberto Chil was responsible for designing and testing the case studies; All authors were responsible for conceptualizing the framework, writing, editing & reviewing the paper.)

[6] Perez-Benito, D., R. Herrera, **R. Chil**, G. Konstantinou, J.M. Udias, M. Desco, and J.J. Vaquero. 2017. "Proposal for a PET Scanner with 4π Formula Steradian Span." In *2017 IEEE Nuclear Science Symposium and Medical Imaging Conference (NSS/MIC)*, 1–4. IEEE. <https://doi.org/10.1109/NSSMIC.2017.8532648>.

(Author Contributions: Rigoberto Chil was responsible for designing and testing the case studies; All authors were responsible for conceptualizing the framework, writing, editing & reviewing the paper.)

Patents:

[7] Konstantinou, G. Vaquero, J, J. **Chil, R.** and Desco, M. Celda Centelleadora. ES2665888B1, issued 2016. <https://patents.google.com/patent/ES2665888B1/>.

(Author Contributions: Rigoberto Chil was responsible for designing and testing the case studies; All authors were responsible for conceptualizing the framework, writing, editing & reviewing the patent.)

The work carried out in all publications is partly included in this thesis in Chapters 3, 4 and 5.
The material from these publications are not singled out with typographic means and references.

SUMMARY

Nuclear medicine is the medical field that studies the different applications of radiation for the treatment and diagnosis of disease. In particular, nuclear medicine imaging is the imaging modality with the highest specificity. The small amounts of radiotracer injected to the patients in these studies are enough to identify lesions that would not be detected with other procedures.

Preclinical imaging plays a decisive role in the development of new drugs and treatments. Animal studies, although controversial, are a necessary evil to ensure the safety and effectiveness of new therapies. The main difficulty of preclinical scanners is that they require higher resolution and better sensitivity than human systems, due to the size of the animal.

In recent years silicon photomultipliers(SiPM) have become the detector of choice over photomultiplier tubes(PMT) on new scanners. SiPMs have proven to be more sensitive than PMTs, smaller in size and are not affected by magnetic fields in the same way that PMTs are. SiPMs are easier to manufacture than PMTs, and can be made into different shapes and sizes, making it possible consider new detector geometries that can potentially improve sensitivity and resolution of current designs. Whole body scanners, able to cover the entire the human body, that seemed impossible some years ago are now a reality and so are the benefits that come with them, an improvement in resolution and sensitivity that directly reduces the dose and the time required for these studies.

Dosimetric studies are mandatory on all radioactive facilities, hospitals, nuclear power plants, etc. Dosimeter use is required for all radiation exposed personnel. An electronic dosimeter, that provides real time measurements and localization, can generate alerts as soon as an increase in radioactivity is detected, improving the safety of the workers exposed to radiation. Although a dosimeter may seem not a very complex device, it is complex enough to serve as a good testing platform for radiation detectors. In this work we developed an electronic dosimeter that has proven able to provide clean energy spectra in real time. These spectra can be used not only to measure the dose, but also to identify the radioactive isotopes generating it. This dosimeter allowed us to prove not only that SiPMs are a good candidate for PMT replacement, but also that most of the electronic designs used for PMTs work for SiPMs as well.

A radiation detector for positron emission tomography (PET) should provide good energy and position information, such that these data can be used to reconstruct an image. The requirements for preclinical systems are more strict than those for human scanners. In this thesis we developed SiPM based detectors that can clearly distinguish the scintillator pixels on a scintillator array of 1.38 mm pixel pitch. The energy resolution of these detectors is 13.37, facilitating a proper detection of the 511 keV photons used in PET

imaging. These detectors were used in the construction of a ring to acquire tomographic images. With this ring configuration we were able to reconstruct a point source of 1.3 mm placed in the center of the field of view.

To overcome the limitations of current PET scanner designs, we proposed a new geometric configuration, based on an icosahedron, with the aim of improving the solid angle coverage of the system. This improvement in coverage has a direct impact in sensitivity and resolution, resulting in a more sensitive and accurate scanner. We introduced as well the use of new detector and scintillator geometries, that helps us achieve a more sensitive and precise scanner. A new SiPM based detector with an hexagonal shape was developed in this work. Thanks to the use of an application specific integrated circuit (ASIC) we were able to create a detector that can distinguish pixels of 1.28 mm pixel pitch, the results were good enough to even consider the use of smaller pixels.

Keywords: Nuclear Medicine, SiPM, PET, Radiation Detector, Preclinical Imaging

CONTENTS

1. MOTIVATION, OBJECTIVES AND THESIS OUTLINE	1
1.1. Motivation	1
1.2. Objectives.	1
1.3. Thesis outline.	2
2. NUCLEAR MEDICINE TECHNOLOGY BASICS	4
2.1. Physics in nuclear medicine	4
2.1.1. Radioactive Decay	4
2.1.2. Beta Decay	4
2.1.3. Interactions of Photons with matter.	6
2.1.4. Radiotracers	8
2.2. Radiological Protection	9
2.2.1. Radiation and Dose	10
2.2.2. Radiation Exposure and Safety Measures	11
2.3. Radiation Detectors	11
2.3.1. Scintillators	12
2.3.2. Photodetectors	14
2.4. PET Scanner	19
2.4.1. Event classification and timing	19
2.4.2. Dead Time and Pile Up	21
2.4.3. Spatial Resolution Limitations in PET	21
3. PERSONAL ELECTRONIC DOSIMETER	24
3.1. Personal Dosimetry Systems	24
3.2. System Description	25
3.2.1. Detector and Scintillator Crystal	26
3.2.2. Signal Processing and Data Acquisition Electronics	27
3.2.3. Communications and Digital Processing.	29
3.3. First Working Demonstrator.	30
3.3.1. Detector	31

3.3.2. Digital Communications and IT Infrastructure	32
3.3.3. Signal Processing and Data Acquisition Electronics	34
3.3.4. Testing the System	36
3.4. Latest Working Prototype	38
3.4.1. Detector	38
3.4.2. Analog read out electronics	39
3.4.3. Communication and peripherals	42
3.4.4. Testing the system	43
4. SIPM BASED SMALL ANIMAL PET RING PROTOTYPE.	45
4.1. PET detector electronics.	46
4.1.1. SiPM Biasing.	47
4.1.2. Multiplexing Network	50
4.1.3. Active Stage	54
4.2. Power distribution board.	55
4.3. Acquisition System	58
4.3.1. Charge Integration Data Acquisition System	58
4.3.2. Real Time Data Acquisition System	60
4.4. Detector description	61
4.5. Prototype Design.	62
4.6. Tests and results	65
4.6.1. Point source in the center of the field of view	65
4.6.2. Derenzo-like acquisition.	72
4.6.3. SSLE LYSO array	73
5. ICOPET: A 4π COVERAGE PET IMAGING SYSTEM	76
5.1. Why a full coverage PET system	76
5.2. Geometrical considerations and configuration.	78
5.2.1. brain PET and small animal prototype	82
5.3. hexagonal SiPM detector	86
5.3.1. Encoding schemes for hexagonal detectors	88
5.4. Proposed Readout System Design	90
5.4.1. Real time ADC based system	91

5.4.2. ASIC based design	93
5.4.3. First results: single channel acquisition	96
5.4.4. Analog Multiplexing Output, design and results	98
5.4.5. ASIC	102
5.4.6. ASIC vs Analog	110
6. CONCLUSIONS AND FUTURE LINES.	112
6.1. What lies ahead.	113

LIST OF FIGURES

2.1	Different decay processes, reproduced from [8]	4
2.2	Beta decay and positron annihilation, from [9]	5
2.3	Interactions of photons with matter depending on energy and atomic number of matter, reproduced from [8]	6
2.4	PMT vs SiPM	14
2.5	SiPM Absorption length and quench cycle from [19]	16
2.6	SiPM microcell with a metal-composite quenching resistor fabricated around them, from [17]	16
2.7	SiPM photon detection efficiency, from [17]	17
2.8	Noise reduction in the new SiPM families, from [17]	18
2.9	a) Annihilation process and b) Schematic representation of PET scanner, from [9]	19
2.10	False coincidence events, from [9]	21
2.11	Sampling error, from [20]	22
2.12	Contributions to the spatial resolution, from [20]	23
3.1	General System Description	25
3.2	Preliminary Spectra of ^{22}Na and ^{137}Cs	27
3.3	First front end electronics used	28
3.4	First front electronics, from PET detectors	28
3.5	ADC and charge integration stage	29
3.6	First working prototype fully assembled	30
3.7	^{22}Na Spectrum on the Central Processing App	31
3.8	S10985 - Mechanical drawings and photon detection efficiency	32
3.9	Data packet format	33
3.10	Signal Conditioning and comparator stage	35
3.11	Dosimeter Electronics Scheme	36
3.12	Spectra acquired proving the range of the detector	37
3.13	Comparing the spectra obtained with different ADCs	37

3.14	Outputs of the central processing system during a test at URJC	38
3.15	Signal conditioning electronics 1/2	40
3.16	Signal conditioning electronics 2/2	41
3.17	System Prototype, modular design	42
3.18	Latest working prototype	43
3.19	Spectrum for ^{22}Na and ^{137}Cs	43
4.1	Flood field and image of the detector presented at the NSS/MIC conference of 2015	45
4.2	Flood field and image of the detector presented at the NSS/MIC conference of 2016	46
4.3	SiPM bias circuit used on our detectors	48
4.4	Recommended operating voltages provided by Hamamatsu	50
4.5	Charge distribution network	51
4.6	Pin Cushion effect using the network shown in figure 4.5	52
4.7	Row and columns charge distribution network	53
4.8	Weighted sum and filtering stages	55
4.9	Power distribution board	57
4.10	Two fully assembled detectors and two detector cases	62
4.11	Four detectors in octagon configuration	63
4.12	Detectors on the optics table and 2D robot used for the tests	64
4.13	Flood field images for all 4 detectors	66
4.14	Pixels selected to study the energy resolution on all detectors	67
4.15	Energy resolution on different pixels on the 4 detectors	68
4.16	Spatial resolution of detector 1	69
4.17	Spatial resolution of detector 2	69
4.18	Spatial resolution of detector 3	70
4.19	Spatial resolution of detector 4	70
4.20	Reconstructed point source on different views	71
4.21	Profiles on the different views	71
4.22	Derenzo-like acquisition	72
4.23	Points separated 2.4 mm	73

4.24	LYSO SSLE array of hexagonal pixels with different light guides	74
4.25	Energy spectrum comparison with different light guides on a SSLE LYSO array	74
4.26	Squared LYSO SSLE array using a 4mm light guide	75
5.1	Sampling error on ring based scanners, reproduced from [84]	77
5.2	First human studies results from the Explorer scanner, reproduced from [82]	78
5.3	Platonic Solids, from [85]	79
5.4	Archimedean Solids, from [86]	79
5.5	Twenty face dice and bacteriophages, from [90]	80
5.6	Regular tilings, from [91]	81
5.7	Hexagonal Pixels vs Squared Pixels, from [93]	82
5.8	Proposed PET designs	83
5.9	icoPET face design	84
5.10	Michelogram	84
5.11	Results presented at [102]	85
5.12	Detectors used on the CTA collaboration	86
5.13	Hexagonal detector designs	87
5.14	Hexagonal detector array developed for us by Hamamatsu	88
5.15	Simulation study of hexagonal crystals	89
5.16	Encoding schemes proposed for hexagonal detector arrays	90
5.17	Triroc ASIC, from the Weeroc website[121]	95
5.18	Experimental setup used	97
5.19	Monolithic LYSO Hexagonal crystal	97
5.20	Pixelated LYSO array	98
5.21	Hexagonal LYSO crystal on an hexagonal array	99
5.22	Flood field image of a pixelated array, with 1.4 mm pixel pitch	100
5.23	Hexagonal LYSO crystal on an hexagonal array	101
5.24	Hexagonal SSLE array of hexagonal pixels	102
5.25	TRIROC evaluation board and adapter board for hexagonal SiPM arrays .	103
5.26	Spectrum of the two data outputs offered by the TRIROC ASIC on a monolithic LYSO crystal	104

5.27 Flood field image generated from combining the two outputs, monolithic LYSO crystal	105
5.28 ASIC channels that fired together on a monolithic LYSO crystal	106
5.29 Energy spectrum using a squared pixel array with the TRIROC ASIC . . .	107
5.30 511 keV photopeak on the Low Gain ASIC output	107
5.31 Flood field image of a 1.3 mm pitch array	108
5.32 ASIC channels that fired together on a 1.3 m pitch array	109
5.33 ASIC vs Analog encoding using a 1.3 mm squared array	110

LIST OF TABLES

2.1	Interactions of photons with matter	8
2.2	Radiotracers used on nuclear medicine	9
2.3	Dose Limits according to the IAEA [12]	10
2.4	Scintillators used in nuclear medicine, data from [16]	14
3.1	S10985 specification	32
3.2	S12573 specification	39
4.1	SiPM Power supply comparison	56
5.1	Electrical and optical characteristics, hexagonal MPPC array	88

1. MOTIVATION, OBJECTIVES AND THESIS OUTLINE

1.1. Motivation

Life expectancy across the globe is and will keep on rising [1], at the same time the birth rates in the more industrialized countries have been below 2-1 children per woman (below replacement level) over the last years [2]. As a result of these two facts, the population in these countries is ageing and so the disease burden of age related diseases is on the rise as well[3].

To fight this age related diseases we will need more and better tools than what we have today. These tools will come in the form of new technologies that will help clinicians to improve the detection and treatment of disease. Cancer is the second leading cause of death globally, over the last 50 years there has been an increase in the incidence rate on cancer, but if we look at the data for the last 10 years we can see a decrease in the mortality rate[4]. Without any doubt, the technological advances in the field of biomedical engineering played an important role in this decrease.

Medical imaging plays a crucial role in the early detection of cancer, it is well known that early detection in cancer increases considerably the survival chances of the patient. Medical imaging scanners are not only used in clinical routine, preclinical studies are also very relevant since they are used in research and drug development [5],[6].

There is still room for improvement in the area of medical imaging research. As researchers is our goal to put our best efforts and hope to contribute no matter how small our contribution might be to the betterment of our technology so that it can aid us in the fight against the effects of ageing and disease.

1.2. Objectives

The work presented in this thesis has been carried out at the Biomedical Imaging and Instrumentation Group of the Universidad Carlos III de Madrid. This group works with different medical imaging modalities covering from advanced image processing for the study of quantitative biomarkers to the design and development of new detectors for medical imaging scanners. This thesis focuses on the latter part, the design of radiation detectors making use of new technologies that improve the image quality of current scanners, more specifically in the area of Nuclear Medicine.

This thesis involves different applications of nuclear medicine, starting from one of the most basic measurement devices, an electronic dosimeter, all the way up to the design of a novel PET detector built using a new detector geometry. We started small and went up so that we could assure the foundations for the technology we were building. For that

reason, we first built a simple dosimeter to start our work with Silicon Photomultipliers, a new technology with which our group had not much experience. Then, we move up to a fully working small imaging PET prototype. Once we had a working PET scanner prototype we look for new areas of improvement in the scanner design, and we saw an opportunity in improving the solid angle coverage of the scanner and even went a step further to propose the use of detectors with non conventional geometries.

The main goal of this thesis is to evaluate the use of the new family of silicon based photodetectors, silicon photomultipliers (SiPMs) on radiation detector for nuclear medicine practice. The specific objectives of this thesis are the following:

1. Develop a system that can be used as a test platform for testing SiPMs as radiation detectors
2. Redesign this test system into a demonstrator (working device) intended for nuclear medical practice
3. Investigate the use of SiPMs for PET detectors
4. Implement a proof-of-concept in the form of a detector ring that can be used for small animal imaging using the new detectors technology
5. Validate the proper working of the system by doing 3D-PET imaging
6. Propose a new PET scanner concept that achieves better sensitivity and spatial resolution than the state-of-the-art
7. Conceive a new detector approach that can be used as the basic block of the future scanners

1.3. Thesis outline

The structure of this thesis is as follows

Chapter One covers some of the basic principles of nuclear medicine, covering the physics and the parts of a detector and how they affect the quality of the measurements required in nuclear medicine procedures.

Chapter Two presents a prototype for a dosimeter with isotope identification and localization capabilities. One of the main purposes of this work was to explore backward compatibility of the new kind of detectors with electronics used in the past with the purpose of creating a direct replacement with enhanced performance.

Chapter Three introduces a new concept for a small animal PET scanner. The chapter starts with the analysis of the electronic performance required, followed by the description of the a real time data acquisition system. We also present alternative acquisition method based on older approaches that may offer even better than current system in terms of

power consumption when used with the new SiPMs. Afterwards, we offer a description of the detectors used on the demonstrator and a thorough characterization of said detectors. Finally, we present some 3D images acquired to evaluate the resolution of the proposed scanner.

Chapter Four describes a new concept for a small animal PET scanner with a solid coverage angle of almost 4π . It starts with a brief discussion regarding the rationale behind the selection of this particular geometry. Then, we offer our vision of a fully working system that fulfills all the requirements for a scanner with such a particular geometry. Finally, we show the results and the progress made on these detectors, the most basic and fundamental elements, of the scanner we aim to create.

Chapter Five presents the conclusions of this work and the future lines of work that lie ahead.

2. NUCLEAR MEDICINE TECHNOLOGY BASICS

2.1. Physics in nuclear medicine

2.1.1. Radioactive Decay

An unstable nucleus will try to reach stability by emitting energy from its nucleus in the form of photons, electrons or other particles. This process by which the nucleus is transformed into a more stable one is called radioactive decay and it is one of the physics principles on which PET is based. Natural radioactivity was first discovered in 1896 by Henri Becquerel in potassium uranyl sulfate [7].

There are different kinds of radioactive decay, for PET the most relevant decay is positron decay β^+ . β decay will be explained in detail in the next section. A graph summarizing the different decay processes is reproduced from [8].

Fig. 2.1. Different decay processes, reproduced from [8]

2.1.2. Beta Decay

In this radioactive decay, a proton from the nucleus will be transformed into a neutron and a positron. A positron is an electron with a positive charge, also known as a β^+ particle. The process can be described as:

$$p^+ \rightarrow n + \beta^+ + \nu$$

In standard notation it will be :

$${}^A_ZX \longrightarrow {}^A_{Z-1} + \beta^+ + \nu$$

The positron will interact with the matter surrounding the nucleus once it is ejected from it. As a result of this interactions, also termed collisions, it will lose energy until it collides with an electron. From this positron-electron collision a new atom will be created named positronium, this is an atom with a lifespan of 10^{-10} seconds. The positron and the electron will be combined in a reaction known as a annihilation event. The distance travelled by the positron until it annihilates is called the positron range, a very important factor in PET imaging, since it will affect the image quality.

During annihilation the mass of both particles, the positron and the electron, will be converted in to two photons. This new photons will both have an energy of 511 keV each, equivalent to sum of both original particles combined 1.02 MeV. This photons will travel form the place where the annihilation event occurred with in exactly opposite directions, 180 degrees apart from one another.

Fig. 2.2. Beta decay and positron annihilation, from [9]

These two photons emitted in exactly opposite directions are very important for PET imaging since they will be the basis for the detection of "coincidence events". Meaning that two particles are detected at more or less the same time on two opposing detectors.

2.1.3. Interactions of Photons with matter

Interactions between radiation and matter depend on both the nature of the radiation and the composition of the matter against which the radiation particles strikes, mainly on its atomic number. There is an energy transfer between the incoming particle and the stopping matter. In some cases the particle loses all of its energy as a result of the interaction, in this case we can say that it has been stopped by matter. It can also be the case that not all energy is absorbed by matter, in this case the particle will travel through matter.

In this chapter only the interaction of photons with matter will be studied, since they are the most relevant for nuclear medicine. The gamma rays used in nuclear medicine have energies from 50 keV to 550 keV, the two predominant interactions are Compton Scattering and Photoelectric Effect[8]. The type of interaction depends on the atomic number of the matter, Compton Scattering is prevalent on matter with lower atomic number (human tissue), while Photoelectric Effect is the most common interaction in matter with high atomic number (shielding elements, like lead). Pair production is presented as well on this section for completeness sake.

Fig. 2.3. Interactions of photons with matter depending on energy and atomic number of matter, reproduced from [8]

Compton Scattering

Compton scattering can be described as a collision between a particle and an electron on the outer shell of an atom, thus with low binding energy. The incident photon transfers only part of its energy to the outer electron. The photon will then be scattered, the scatter-

ing angle depends on the energy lost during the interaction with the electron, according to the equation:

$$(E_{sc} = E_{\gamma}/(1 + (E_{\gamma}/0.511)(1 - \cos\Theta))$$

This is, strictly speaking, a photon-electron interaction, implying that the amount of energy to be transferred will not depend on the properties of the absorbing material [10].

Compton scattered photons can be eliminated from the list of coincidences in PET imaging by using energy discrimination techniques.

Photoelectric Effect

In the photoelectric effect the atom absorbs all the energy of the incoming photon. The atom uses this energy to eject an orbital electron, this ejected electron is known as a photoelectron. The kinetic energy of this the photoelectron will be the difference between the incoming photon energy and the binding energy of the electron.

$$E_{ph} = E_{\gamma} - E_b$$

The photoelectron leaves a vacancy in an inner shell layer, this vacancy will be covered by an electron from an outer shell, the excess energy produced as a result of this will be emitted as an X-ray(Auger Electron).

Pair Production

Pair production occurs only with particles that have an energy higher than 1.02MeV (2x 511 kev). The interaction is most likely to happen with the nucleus of the absorbing atom, as a result of it, a pair of electrons with positive and negative charge are produced at the expense of the incoming photon. Excess energy left after the creation of the electron pair is transferred as kinetic energy to the electron pair.

$$E_{e+} + E_{e-} = E_{\gamma} - 1.02MeV$$

The positron will then undergo an annihilation event with an electron, once it has lost its kinetic energy. As a result two annihilation photons with energies of 511 keV and opposite directions will be emitted.

In soft tissue pair productions is not very relevant for energies below 10 MeV [7].

Interaction	Secondary Photons	High Energy Secondary Electrons
Photoelectric	Characteristic X-rays	Photoelectrons, Auger Electrons
Compton	Scattered Photon	Recoil Electron
Pair Production	Annihilation photons	Positive-negative electron pair

Table 2.1. Interactions of photons with matter

2.1.4. Radiotracers

An atom can have a radioactive nucleus without it affecting its chemical behaviour, chemical reactions occur between the electrons on the outer orbitals of the atom, whereas radioactive decays involve mainly the nucleus. This will allow a radioactive tracer to have the same chemical and physiological characteristics as its stable counterpart [10].

In nuclear medicine radionuclides are attached to compounds with useful physiological properties, the result is what is known as a radiopharmaceutical. When performing a PET imaging procedure this radiopharmaceutical has to be injected to the patient prior to the exam.

Relevant considerations when choosing a proper radionuclide for a study are:

- Half life : Ideally should be between minutes or hours. Not too short so it can be produced, distributed and injected to the patient on time, but also not too long to avoid unnecessary exposure once the exam has finished.
- Specific Activity: Mass of radionuclide that needs to be added in order to get a certain level of radiation dose. Ideally we should use as little mass as possible, working always on subpharmacologic tracer doses.
- Type and energy of emissions: Ideally we will want to work with photons that can leave the body, allowing us to detect them from outside, with a medical imaging system. This means photons with energies in the range of 50-550 keV.
- Radionuclidic purity: Amount of the total radiation that is in the form that we need for our study. Purity should be as high as possible, this will allow us to reduce the imaging time and the dose delivered to the patient.
- Chemical Properties: Radionuclides that can be used to create a wide range of labeled products, elements for which it is easy to obtain a precursor are preferred when creating radiotracers.

Radionuclide	Half Life	Radiopharmaceutical	Measurement	Clinical Use
^{82}Rb	1.25 min	^{82}Rb -rubidium chloride	Myocardial perfusion	Coronary artery disease
^{18}F	110 min	^{18}F FDG	Glucose metabolism	Cancer, neurological disorders and myocardial disease
^{99m}Tc	6.02 hr	^{99m}Tc -MAG3	Renal function	Kidney Disease
^{123}I	13.2 hr	^{123}I -sodium iodide	Thyroid function	Thyroid disorders

Table 2.2. Radiotracers used on nuclear medicine

2.2. Radiological Protection

The main goal of radiological protection is to establish standards that ensure the safety of everyone exposed to radiation. Radiological protection measures intend to control and regulate the use of radiation and its effects on the environment, including minimizing the dose received by the population.

In this context all radiation exposure must be specifically justified, it must produce a measurable benefit to society as a whole. A very important concept is the ALARA principle, it states that radiation exposure should always be kept "As Low As Reasonably Achievable" [11].

To ensure that radiological protection measures are followed, each country has their own legislation regarding radiation safety, in Spain, it is the "Reglamento de Protección Sanitaria contra Radiaciones Ionizantes (Real Decreto 783 /2001)". There is also an International Commission of Radiological Protection(ICRP), this commission will dictate the guidelines to be followed regarding radiological protection. There is also the International Atomic Energy Agency (IAEA) it will publish standards that must be met, generally this standards follow the ICRP recommendations. In Europe there is also a treaty, EUROATOM, that dictates the requisites regarding radiological protection that all European Union member countries must follow. Finally each country can create their own legislation regarding radiological protection, but it must always comply with what is stated on EUROATOM, it can be more restrictive, but not less. In Spain the Nuclear Safety Council (CSN in Spanish) will be the governmental agency ensuring that radiological protection rules are followed.

Application	Occupation	Apprentice or Student	Public
Effective Dose	20 mSv per year averaged over 5 years, maximum of 50 mSv in a single year	6 mSv per year	1 mSv per year
Annual Equivalent Dose in:			
Lens of the Eye	20 mSv	20 mSv	15 mSv
Extremities	500 mSv	500 mSV	–
Skin	500 mSv	500 mSv	150 mSv

Table 2.3. Dose Limits according to the IAEA [12]

2.2.1. Radiation and Dose

Radioactive principles were already explained in section 2.1, but to simplify and summarize it we can state that a radioactive atom is an atom that emits particles in order to achieve a more stable state. The radiation emitted by these atoms can be classified in three main types of particles: alpha, beta, and gamma particles, they will each have different energies and interact differently with matter. These charged particles can interact with matter producing ionization on the atoms of said matter. When ionization occurs on tissue it can lead to DNA alterations, DNA alterations will translate into abnormal cell development.

Some tissues are more sensitive to radiation than others, thus when measuring the dose perceived we will need to use a weighting coefficient to compensate for this sensitivity difference. Radiation dose is measured in Sieverts (Sv), but it's more frequent to see smaller fractions like milliSievert (mSv) or even microSievert (μSv). When measuring dose, there are three different dose measurements, absorbed dose, equivalent dose and effective dose.

Absorbed Dose Total energy deposited by radiation for each unit of mass of tissue.

Equivalent Dose Same as the absorbed dose but taking into account the type of radiation absorbed.

Effective Dose Same as the equivalent dose but taking into account the sensitivity of different organs and tissues to radiation.

The effective dose is commonly referred as "dose" in the context of radiological protection since it is the most complete of all measurements.

2.2.2. Radiation Exposure and Safety Measures

Radiation produces two different kind of effects, those we can assure will occur at high exposure levels (deterministic effects) and the ones that can always happen but their probability increases with the dose (stochastic effects). Stochastic effects are more difficult to predict and control and are the reason why the safety levels for the general population are so low.

Radiation can come from man made sources like medical imaging equipment or nuclear reactors, but it can also come from nature, as is the case with cosmic radiation. Natural occurring radiation is more difficult to prevent and control than the radiation coming from artificial sources.

Some occupations require being exposed to radiation as part of their daily activities, this exposure is known as occupational radiation. There is also medical exposure, the radiation coming from medical exams or treatments. Finally there is general population exposure, covers all radiations exposures not considered in the other two, it also includes the radiation coming from natural sources.

To limit unnecessary exposure there are three main safety measures that must always be followed specially by radiation exposed personnel:

- **Shielding:** Proper shielding materials can completely eliminate the exposure to a certain source. These materials should be chosen according to the radiation type. Alpha particles can be stopped by a sheet of paper or the human skin, so they are specially dangerous if ingested. Beta particles on the other hand can be stopped by wood or a metal sheet. Gamma particles require better shielding, needing leaded walls or thick concrete walls.
- **Distance:** Radiation and distance follow the inverse square law. Exposure at a distance diminishes as we move further away, at a ratio proportional to the square of the distance from the source. Just by staying at a certain distance from a radioactive source we can significantly reduce the dose.
- **Time:** It is clear that if we limit our exposure time the perceived dose is also limited. For this particular reason all radiation exposed personnel should try to stay exposed to a source for as little time as possible.

2.3. Radiation Detectors

Radiation detectors are a fundamental element in nuclear medicine. They provide us with the dose measurement information needed to ensure the safety of radiation exposed

personnel and they are also used for image acquisition in both PET and SPECT.

Radiation detectors are sensors capable of producing a measurable signal as a result of a radioactive interaction. On section 2.1, we covered the basics of the interactions of radiation with matter. As a result of this interactions radiation energy is transferred to the interaction medium by ionization and excitation. These ionization events will end up producing charge carriers. We can distinguish radiation detector according to their the operation principle[11]:

- Gas- Filled Detectors: Electrons and ions are produced in a gaseous medium
- Semiconductor Detectors: Electrons and holes are produced in a semiconductor material
- Scintillation Detectors: Light is emitted in a scintillator material.

We focus on the later kind of detectors, scintillator based detectors, since they are the ones used on this thesis and the most common kind of detector used on nuclear medicine imaging.

A standard scintillator based detector is based on three building blocks:

- Scintillator: Material with a very high atomic number, so it has high stopping power. The scintillator not only stops the incoming photon but it also emits light, the amount of light emitted is proportional to the energy of the incoming photons.
- Photodetector: Sensing element capable of transforming the light emitted from the scintillator into an electrical signal. It is basically a very precise and sensitive light sensor. In the past the most used detectors were Photomultiplier Tubes (PMTs) but that is changing giving place to a new family of detector based on silicon, Silicon Photomultipliers (SiPMs).
- Front-End Electronics: Electronic signal conditioning elements used to boost the level and SNR of the signal from the photodetector. Since event position information is essential, in most systems a charge distribution network is used to minimize the number of analog output channels [13].

2.3.1. Scintillators

Most materials dissipate the energy produced from radiation interactions as thermal energy, scintillators are materials in which a fraction of this energy is emitted as light. There are two main kinds of scintillators, inorganic scintillators (solid crystals) and organic scintillators(liquid). The light from a scintillation event is proportional to the energy deposited by the incoming particle. The amount of light produced is in the order of a hundred to a few thousand of photons per radiation interaction, this small amount of light makes it necessary to have light detectors with a very high sensitivity.

Inorganic scintillators are the most frequently used on nuclear medicine detectors. Scintillation is due to the crystal structure of inorganic scintillators, individual atoms or molecules of the same substance do not scintillate. Some crystal can scintillate in their pure state, but they might require special conditions to do so. For this reason, impurities called activators, are added to the scintillator crystals to ease the scintillation process. A good example is NaI, this crystal scintillates in its pure form only at very low temperatures, but if thallium is added producing a NaI(Tl) scintillator it can scintillate at ambient room temperature. NaI(Tl) scintillators are the most commonly used scintillators in nuclear medicine[10].

When choosing a proper scintillator there are some properties to consider[14]:

- Stopping power: Probability that the particle will be stopped by the scintillator. It depends on the effective atomic power, obtained as a weighed sum of all the elements forming the crystal. The higher the better.
- Decay time: Timing properties of the light pulses coming from the scintillator depend on the decay time. The faster the scintillator is, the better our timing resolution will be. It also influences the maximum count rate of our detector.
- Emission spectrum: should match the quantum detection efficiency of the sensor to be used. Ideally the emission peak of the scintillator and the maximum detection efficiency of the detector will have the same wavelength.
- Refractive index: it is important that the refractive index of the scintillator and the input surface of the sensor are as close as possible to minimize light loss. Normally grease or glue is used to avoid any air gaps between scintillator and detector, the refractive index of the chosen glue or grease should also be in the same range.
- Transparency: it is important that the scintillator is transparent to its emission wavelength so that as much light as possible reaches the detector
- Linearity: to obtain a good energy spectrum the light emission should be proportional to the deposited energy, at least over a certain range.

As we mentioned before, NaI(Tl) is the most commonly used scintillator in nuclear medicine, this is true when the energies of interest are in the range of 50-250 keV[10], but as we go for higher energies, like the 511 keV used in PET, denser scintillators are needed. The most commonly used scintillator for small animal PET detectors is LYSO[15] a cheaper version of LSO with very similar properties.

Scintillator	Light Yield (photons/keV)	Decay time (ns)	Peak emission (nm)	Refractive Index	Density g/cm ³	Hygroscopic
NaI(Tl)	38	250	415	1.85	3.67	Yes
CsI(Tl)	54	1000	550	1.79	4.51	Slightly
LYSO	33	36	420	1.81	7.1	No
BGO	8-10	300	480	1.79	7.13	No
LaBr ₃ (Ce)	63	16	380	-1.9	5.08	Yes

Table 2.4. Scintillators used in nuclear medicine, data from [16]

2.3.2. Photodetectors

The most commonly used photodetector elements in PET are photomultiplier tubes and silicon photomultipliers. On figure 2.4, we can find a table summarizing the main characteristics of one versus the other.

	PMT	SiPM
MR Comp	No	Yes
ToF	limited	Yes
Gain	10 ⁶	10 ⁶
Temp Dep	No	Yes
Size	large	compact
HV	~1000 V	~ 50 V
ReadOut	analog	analog

Fig. 2.4. PMT vs SiPM

Photomultiplier tubes were the sensor of choice until silicon photomultiplier came along[9]. The trend in new implementations is to use SiPMs[17], although PMTs are still used in some applications. PMTs are widely discussed in the literature [18], [14], but are

not of particular interest to this thesis, so the focus will be placed on SiPMs.

Hamamatsu, one of the main manufacturers of both PMTs and SiPMs, points out some of the advantages of SiPMs when compared to PMTs [17]:

- SiPMs attain a higher quantum efficiencies over a wider range of wavelengths
- SiPMs have better collection efficiency of photoelectron charge (less photoelectric signal loss)
- Fine feature sizes are possible thanks to modern silicon microfabrication processes
- SiPMs operate at lower voltage requiring lower supply currents, resulting in a reduction on power consumption
- Improved high frequency response thanks to the small PN junction and anode/cathode dimensions
- SiPMs can be manufactured with a high fill factor, allowing the construction of plane arrays with ultrahigh packing-efficiency
- SiPMs are not affected by magnetic fields, hysteresis, aging/warm up considerations unlike PMTs

PMTs however still have some advantages over SiPMs like a lower dark current, less capacitance per unit area and better radiation hardness than SiPM.

Silicon Photomultipliers

Silicon Photodiodes The first principle of how silicon based photodiodes work is how photons are absorbed in silicon. When a photon is absorbed in silicon, it transfers its energy to an electron causing it to move from the valence band to the conduction band, creating in this process an electron-hole pair. Silicon photodiodes are semiconductor devices formed by a PN junction with a depletion region free of mobile charge carriers. Applying a reverse bias voltage to this device will accelerate charge carriers towards the end terminals. Depending on the carrier type, holes will go to the anode and electrons will flow to the cathode. Thus a photodiode under a reverse bias voltage will produce a net flow of current if it absorbs a photon.

Avalanche Photodiode When the reverse voltage applied to the diode is high enough, the charge carriers generated will possess enough kinetic energy to create secondary charge pairs, this process is known as impact ionization. Impact ionization is a phenomenon that quickly multiplies the number of charge carriers, similar to an ionization avalanche. This avalanche effect will propagate through out all of the silicon volume in

the photodiode, this means that a single absorbed photon can induce a macroscopic current in the device, this process is known as Geiger discharge, and we can say that this photodiode is operating in Geiger mode.

Photodiodes operating in Geiger mode achieve a high gain, this gain depends on the wavelength of the incoming radiation, the reverse bias voltage applied to it (more voltage, more gain), and it will diminish as temperature increases. To stop the flow of current through the device a passive quenching element is needed, a series resistor R_q is used to limit diode current during breakdown. A photodiode operating in Geiger mode works like a photon activated switch, this is a problem since if two or more photons were to arrive at the same time the output signal will be the same as for only one photon.

(a) Absorption length in silicon

(b) SiPM quench cycle

Fig. 2.5. SiPM Absorption length and quench cycle from [19]

Silicon Photomultipliers APDs are great photodetectors but their switch like behaviour limits their usability because they are not able to measure large amounts of incoming light. Silicon photomultipliers are presented as a solution to this problem, a silicon photomultiplier is a dense array of APDs each with their own quenching resistor. Each APD in a SiPM will be referred as a microcell, microcells fire individually when they absorb a photon, allowing the remaining microcells to detect incoming photons. SiPMs can be manufactured with different microcell sizes this impacts on their performance.

(a) Pixel pitch
25 μm

(b) Pixel pitch
50 μm

(c) Pixel pitch
75 μm

Fig. 2.6. SiPM microcell with a metal-composite quenching resistor fabricated around them, from [17]

Now we will discuss some of the main characteristics of SiPMs, that should be taken into account when selecting what device to use for a particular application.

Photon Detection Efficiency (PDE) Photon detection efficiency tell us how sensitive a SiPM is, it depends mainly on two parameters: The wavelength of the sensed light and the overvoltage applied to the device. PDE is the probability that a photon reaching the SiPM sensitive surface will produce an avalanche. Since microcells presents the switch like behaviour previously mentioned, detectors with smaller microcells and higher fill factors present better PDE.

Fig. 2.7. SiPM photon detection efficiency, from [17]

The most important detail is that the PDE sensitivity peak is as close as possible to the emission peak of the scintillator used in our detector.

Breakdown Voltage and Overvoltage Breakdown voltage is the voltage that needs to be applied to the device in order to generate an electric field in the depletion region with enough strength to ensure that the device operates in Geiger mode.

SiPMs are operated at a value higher than the breakdown voltage to ensure the sensitivity and the proper working of the device, the difference between this operating voltage and the breakdown voltage is known as overvoltage.

Gain and pulse shape SiPM gain is the charge created by detected photon, the main factors affecting the gain are overvoltage, microcell size and temperature. Operating the SiPM at a greater overvoltage value gives it more gain but it will also increase the dark counts making the sensor more noisy. SiPM gain increases with microcell size, bigger

microcells have more capacitance. Temperature has a negative effect in SiPM gain, for this reason is very common to see temperature compensation schemes on SiPMs, however on the newer SiPM families this effect has been greatly decreased.

SiPM pulses have two main components a rising part and a recovery time. The rising part is a very fast peak, rise time is a very important parameter for timing in SiPMs and depends on the output impedance of the sensor and its packaging. On the other hand, recovery or decay time depends on microcell capacitance, quenching resistor value, and number of microcells present in the detector. Microcell capacitance is related to its size, larger microcells having more capacitance, so larger microcells have longer recovery times than smaller ones.

Noise sources: Dark Counts, Afterpulsing and optical crosstalk Dark counts are avalanches produced without any photon arriving to the detector, they are due to thermally generated electrons. SiPM microcells fire due to this thermal noise. Manufacturers give a measure of the rate of dark counts as a function of overvoltage and temperature which are the two main factors in dark counts.

Some carriers can be trapped in the silicon during the breakdown process, these carriers can later on initiate a new avalanche process, producing smaller amplitude pulses after the main pulse. These pulses produced by trapped carriers are called afterpulses and like dark counts, worsens with overvoltage and temperature.

Crosstalk is the probability that, when a photon is detected in a microcell, the avalanche produced by the detection can create photons that induce an avalanche on a neighbouring microcell. Optical crosstalk depends on the overvoltage applied and the fill factor of the detector.

Manufacturers are working on improving these noise parameters, as can be seen on figure 2.8, however we still need to be careful when selecting the overvoltage value to work with our detectors, since as has been seen it is the main source of noise on SiPMs.

(a) Reduction in dark counts (b) Reduction in afterpulses (c) Reduction in crosstalk

Fig. 2.8. Noise reduction in the new SiPM families, from [17]

2.4. PET Scanner

As a brief recap lets remember the most important physics phenomena for PET, annihilation events. When a radioactive atom emits a β^+ particle, this particle annihilates with a neighbouring electron producing two photons that travel in opposite directions with an energy of 511 keV both. In PET imaging we need to detect this two photons in order to establish what is known as a Line of Response. For this reason the most common PET configuration is a ring of detectors surrounding the patient where there is always one detector opposed to another facilitating the creation of response lines.

Fig. 2.9. a) Annihilation process and b) Schematic representation of PET scanner, from [9]

We will now present a brief overview of some of the concepts and terminology used on PET imaging.

2.4.1. Event classification and timing

Coincidence Time Window A time window is established so that events can be considered to be in coincidence when they arrive with a time difference below said window. The selection of a proper time window is a very important factor on a PET acquisition, using a smaller window might make us lose more events, but using a very large window might add false coincidences that will translate into noise in our reconstructed image.

Singles Singles are those events for which there is not another coincidence event occurring inside the time window. Singles are specially useful for detector characterization and are generally discarded when acquiring a PET image dataset, since they can not be used for the reconstruction.

Coincidences Events that arrive at opposite detectors in a time shorter than the coincidence window. These events are commonly stored together and used to obtain the lines of response. Only coincidence events provide useful information for PET image reconstruction.

tion. Care must be taken to not include false coincidences in a dataset since it will lead to noise in the final image.

Depending on the data acquisition and processing scheme used on the PET imaging system, singles might be stored together, in a file commonly referred to as listmode. Listmode data is used later on to detect coincidence events using an algorithm known as coincidence sorter that goes through the list of all acquired singles to find those that fall inside the same coincidence time window. This acquisition scheme does not seem so bad at first, since it ensures that all information is kept until the processing stage. However the problem with this is that if a real time acquisition scheme is used on a system with a large number of detectors the ratio of coincidences to singles might be relatively low and the waste on bandwidth and processing power might end up being a bottleneck on the maximum number of counts per second that the system can acquire.

Another option is to attempt to detect which events are coincidence events at the lowest possible level thus storing only the useful coincidence events information, this can be done thanks to the real time processing capabilities of FPGAs and modern microprocessors.

False Coincidences One of the noise sources on PET are false coincidence events, there are two types of these events, scattered events and random coincidence events:

- **Scatter Events** Sometimes one of the photons from the annihilation event undergoes Compton scattering, and as a result of this interaction its trajectory is modified. This Compton scattered photon ends up producing a false response line. A way of minimizing this problem is by using a tightly adjusted energy threshold in an attempt to discard all events with an energy different than 511 KeV, how good we can adjust this is dictated by the energy resolution of our detectors.
- **Random Coincidences** There is also the case in which two simultaneous annihilation events occur with two photons from different events reaching the detectors and creating a false line of response. The best way to correct this is to use a coincidence time window as small as possible.

Fig. 2.10. False coincidence events, from [9]

2.4.2. Dead Time and Pile Up

The time it takes the system to process an incoming event and be ready for the next radiation event is known as dead time. Dead time directly impacts on the maximum count rate that the system can process. Dead time depends on the signal processing chosen, systems that use shaping to adapt the signals to slower ADCs or systems based on charge integration suffer from worse dead times than real time acquisition systems.

Pile up is what happens when an event arrives while another event is being processed, as a result of this the energy and position measurements for both events will be wrong. Pile up events increase with the activity of the tracer used, for this reasons systems that can handle high doses need to ensure a dead time as low as possible. The common procedure is to detect when a pile-up event has occurred and discard said event.

Dead time and pile up events gives us an estimate on the maximum dose that the system is able to handle by measuring the maximum count rate for the system.

2.4.3. Spatial Resolution Limitations in PET

The limits for spatial resolution in PET are dependent on several factors some of which we can control, like detector configuration and decoding scheme and other that are more difficult to control like the positron range of radiotracers. In [20] the author proposed the following equation to measure the limits of spatial resolution in PET, the equations here presented are valid for a PET scanner with a ring topology (the most common).

$$(\Gamma) = 1.25 \sqrt{(d/2)^2 + s^2 + (0.0044R)^2 + b^2 + \frac{(12.5r)^2}{r^2 + R^2}} (mm fwhm)$$

In this equation each of the terms refers to a different factor affecting the spatial resolution. To explain each of the terms we will express it as:

$$(\Gamma) = A \sqrt{B^2 + C^2 + D^2 + E^2 + F(mm.fwhm)}$$

- A Refers to the sampling error. This error comes from the fact that the lines of response in a conventional PET scanner do not cover the field of view evenly.

Fig. 2.11. Sampling error, from [20]

- B Most PET detectors use scintillator arrays, event position can be assigned to a particular crystal element in the array but it is not possible to position the event precisely inside the scintillator. This error is due to the detector size, it is $d/2$, being d the width of the detector element.

- C Error induced by the positron range, it has already been mentioned in section 2.1.2, that the distance travelled by the positron before annihilating depends on the radioisotope producing the positron.

- D Photons produced by an annihilation event are emitted theoretically at 180° degrees apart, but in practice there is a small acollinearity error between them of 0.2° FWHM. This produces a blurring effect proportional to radius of the PET imaging system, estimated at $0.0044R$.

- E PET detectors have a high number of input channels, but not all of these channels can be digitized, to minimize the number of analog output channels analog multiplexing techniques are used. This multiplexing degrades spatial resolution and can be estimated at $d/3$, where d is the width of the detector element.

-F A photon can interact with a different crystal than the one it entered from, as a result said photon will be assigned to a wrong line of response, this effect worsens as the source is positioned outwards(r) inside the detector ring. This effect is also affected by the radius of the ring (R). This penetration error is described by:

$$\frac{12.5r}{\sqrt{r^2 + R^2}}$$

On the previous equation the reconstruction error is not taken into account, but this error depends on the algorithm used. Reconstruction algorithms are not covered in this thesis, but they are vastly described in literature[21],[22],[23],[24].

Fig. 2.12. Contributions to the spatial resolution, from [20]

3. PERSONAL ELECTRONIC DOSIMETER

Our group had already started to work with SiPMs [25], but we needed a system we could use as a testbench to start transitioning from detectors based on PMTs to detectors based on SiPMs, the new technology. We saw a good opportunity to accomplish this by building a dosimeter, a relatively simple system compared to a detector, but complex enough that would allow us to test most of the electronics that we could later on use on a PET detector. The electronic dosimeter presented here is part of a larger system that includes, the personal dosimeter, a wireless gateway and a central processing system. It is designed using a combination of a scintillator crystal and the new SiPM (silicon photomultiplier) technology that allows for a more compact and precise radiation detector. This dosimeter includes all the necessary elements for signal processing and data acquisition. Acquired data is stored as histograms, keeping several histograms with different time windows. The device uses wireless communication to send the data to a central processing base.

This system is also able to localize the dosimeters both indoors and outdoors. Outdoors localization is based on a GPS module and will only be used when strictly needed, to reduce power consumption. Indoors localization will depend on the wireless gateway to which the personal dosimeter is connected. In the event of a connectivity loss the system will keep storing radiation measurements in its internal memory.

The central processing system will handle incoming histograms from different personal dosimeters thus allowing the generation of reports on radiation distribution and radiation maps. This processing base will include user profiles, so that by assigning each user a dosimeter we can know the dose received by said user.

3.1. Personal Dosimetry Systems

The use of personal dosimetry systems is mandatory for many occupations that involve radiation exposure such as nuclear science researchers, power plant personnel and hospital personnel working in nuclear medicine or radiation therapy[26].

The more commonly used dosimeters are film dosimeters and thermoluminescence dosimeters. These dosimeters measure the dose over a certain period of time. A disadvantage of said dosimeters is that they are not able to perform real time measurements or spectroscopic dosimetry. Studies show that active dosimetry leads to a dose reduction in interventional radiology[27],[28].

There are already several electronic dosimeters on the market, most of them are meant to be used in hospitals[29],[30],[31], some to be used for homeland security applications[32],[33] and only a few similar to the one presented here, which offer a broader set

of applications[34],[35],[36],[37]. Of these devices only two specifically state that they use scintillators[32],[34] another specifies that it is based on silicon diode detectors[37] and a last one is based on Geiger Muller tubes[35]. Most of these devices have some of the characteristics that the device presented on this work has, but lack real time communication and localization: they support some kind of uploading method, but in most cases the dosimeter has to be connected to a PC or a dock station and the dosimetry data has to be uploaded by the user.

The dosimetry system proposed here can also be used as a radiation monitoring system, that will allow to survey radiation levels over wide areas, proving its usefulness for other applications like homeland security. This has been tested comparing with similar systems relying on pulse counting [38],[39] or a combination of drones and radiation imaging devices.[40]

3.2. System Description

The system architecture consists of three elements: the Personal Dosimeter (PD), used for radiation detection, data preprocessing, storage and transmission; a Wireless Gateway (WG), used for indoor localization and communication to the internet when it is not available on the personal dosimeter; and a web-based storage, monitoring and data management system, named Central System (CS), which also allows PD management. The number of WG and PD deployed depends on the application scenario and the required sensor coverage .

Fig. 3.1. General System Description

Personal Dosimeter

The Personal Dosimeter is built using a SiPM radiation detector coupled to a scintillator crystal CsI(Tl) along with the front end electronics needed for radiation pulse processing. The dosimeter includes as well an ADC and a microprocessor allowing it to acquire and process the radiation data. The microprocessor can further enhance the dosimeter capabilities by providing data preprocessing and storage, alarm detection, and wireless communications. The dosimeter also comes with a localization system (GPS based), an internal clock and an ID code for each dosimeter so that it can be identified among different dosimeters. Batteries are chosen so that the system can work for 10 hours on a single charge, depending on the desired network and localization configuration.

The dosimeter stores internally the most recent radiation histogram and a cumulative histogram. Every two seconds the system sends both histograms to any of the available Wireless Gateways. If none are available, the system will keep on storing the acquired information (histograms, time stamps, localization information) in an internal memory until it regains connection. Once the system regains connection, all stored information will be sent.

Wireless Gateway

This module is the communication gateway between the Personal Dosimeters and the Central System. The device can be seen as a wireless router connecting all Personal Dosimeters in its coverage area, it collects all the information coming from the Personal Dosimeters and upload it to the Central System, through an internet connection. For indoor localization, the Wireless Gateway can make use of beacons or use Received Signal Strength Intensity (RSSI) techniques for Personal Dosimeter localization. For outdoors localization, GPS information is preferred.

Central System

The Central System is a remote server containing a database with the incoming histograms from all the Personal Dosimeters in the field. The server also provides the user with a web interface for accessing said histograms, isotope identification and Personal Dosimeter management. This web interface enables remote monitoring in almost real-time depending on the connectivity of the Personal Dosimeter being tested, including localization and generated alarms information. This constant monitoring enables the generation of dynamic isodose maps.

3.2.1. Detector and Scintillator Crystal

A characterization of different combinations of radiation crystal and radiation detector were tested in order to find the optimal configuration[41],[42]. Five different alkaline crystals were tested: LaBr₃:Ce, CeBr₃, NaI:Tl, KI:Tl, CsI:Tl and seven non-alkaline crystals: BaF₂, GSO, BGO, MLS, LYSO, LuAG:Pr, LFS. These crystals were coupled to different radiation detectors, two PMTs: XP2020Q and XP20D0 from Photonis[43] and two silicon based photomultipliers(SiPMs) S10985-50C[44] from Hamamtsu and SPM

Micro30335x13 from SensL[45]. Different readout circuits had to be implemented for the SiPMs since they had different pixel arrangements 2x2 (Hamamatsu) and 4x4 (SensL).

In order to measure the intrinsic activity for each crystal an HPGe semiconductor detector was used. Energy resolution for the crystals was measured by acquiring spectra for ^{22}Na and ^{137}Cs . These measurements were performed using a benchtop multichannel analyzer available (MCA) at UCM.

Fig. 3.2. Preliminary Spectra of ^{22}Na and ^{137}Cs

The conclusion of this study was that the optimal configuration consisted of a $9 \times 9 \times 20 \text{ mm}^3$ CsI:Tl crystal coupled to a S10985-50C SiPM detector from Hamamatsu. This setup gave the best energy resolution, acceptable sensitivity and the crystal's emission wavelength suited well the spectral sensitivity of the photodetector.

3.2.2. Signal Processing and Data Acquisition Electronics

At the same time that the selection of crystal and detector configuration was done, we tried first the same electronics used for PET detectors, that had been previously developed on our group. The idea was to support both slow and fast scintillation pulses. With this idea in mind, two different electronics readouts were developed, one for the slow crystals and one for the fast crystals. The electronic readout for the slow crystals consisted of a shaping circuit using a Cremat amplifier and a fast baseline restoration circuit. This readout was optimal for CZT or detectors with a high RC component (around $5\text{-}100 \mu\text{s}$). The results

from this readout can be seen on figure 3.2.

Fig. 3.3. First front end electronics used

The readout for the fast crystals was more similar to the one already in use on PET detectors. This readout is quite similar to the previous one as it also includes a gain stage and a fast baseline restoration component. However, the amplifiers used in this readout allows us to work with detectors that posses a small RC component (nanoseconds to 5 us).

Fig. 3.4. First front electronics, from PET detectors

When testing the fast readout a charge integration stage was added prior to the ADC conversion. This conversion system requires a very fast switching signal to command

the integration gate as well as the start of the ADC conversion. If any of this signals are delayed we risk losing the rising edge of the pulse on the ADC.

Fig. 3.5. ADC and charge integration stage

3.2.3. Communications and Digital Processing

It was a requirement for this system to be able to sort data on a uSD card in order to keep the acquired histograms in case communications had been lost. As such a first attempt at writing and reading data back from a uSD card was performed using a development kit from Microchip for the PIC18F family of microprocessors. A very important aspect of this device was to include localization data for both indoors and outdoors scenarios since it will enable the generation of dynamic isodose maps, allowing to not only generate alarms when needed but to pinpoint the source of said alarm as well. Outdoors localization was achieved using a COTS platform, the Waspote from Libelium. Tests were conducted satisfactory using said platform with the previously mentioned development platform from Microchip.

For the indoors localization the selected method would be RSSI, in order to test this 3 different wireless communication methods were employed: Bluetooth, Zigbee and Wi-Fi. Another possible solution was to use a GSM module, this however was discarded due to the power consumption of said module when compared to the other wireless technologies.

Wireless communication as well as indoor localization was tested using the Waspote unit. It was possible to establish a reliable connection between the dosimeter and the base units with all of the standards tested, however the data transfer rates obtained were not as high as expected. The limitation on the data rates was found to be on the hardware of the Waspote unit. For this reason on the next designs, this module will not be employed, nevertheless it was very useful for testing the integration between the dosimeter unit and the base units. On this early stages a PC was used as base unit.

3.3. First Working Demonstrator

The previous studies served to assess the feasibility of the system as well as to determine a possible implementation of the system.

Along this line a first system demonstrator was built using the detector and crystal configuration chosen by UCM, readout and data acquisition electronics provided by UC3M and the communication and processing infrastructure by URJC.

Fig. 3.6. First working prototype fully assembled

This system was tested and presented on [46]. Figure 3.7 below displays the resulting spectrum on the Central Processing App.

Fig. 3.7. ^{22}Na Spectrum on the Central Processing App

The prototype consisted of a Personal Dosimeter, built using several peripherals connected to an Arduino Mega board, this is the radiation detection unit, tasked with event acquisition, storage and uplink communication with the wireless gateway. A wireless gateway device, built using a Raspberry Pi, to which several dosimeters could be connected, in indoors situations this system will also take care of the localization using RSSI techniques, the main purpose of this device is to act as a gateway between the personal dosimeters and the central processing system. The central processing system which is basically a web application that can be used to keep track of the data acquired by the dosimeters, it can also perform some higher order functions like dosimeter and user management, isodose map generation, etc. The system is a Java Web App running on a Debian server.

3.3.1. Detector

The detector used for this implementation was the S10985[44] from Hamamatsu together with a CsI(Tl) crystal.

Parameter	S10985
Number of channels	4(2x2)
Effective Area	3x3 mm
Number of pixels/channel	3600
Pixel Size	50x50 μm
Peak Sensitivity	440 nm
Operating Voltage	70 $\pm$ 10 V
Gain	7.5x10 ⁵

Table 3.1. S10985 specification

Fig. 3.8. S10985 - Mechanical drawings and photon detection efficiency

The chosen crystal had a dimension of $9 \times 9 \times 20 \text{ mm}^3$ that coupled nicely with the sensitive area of the detector.

3.3.2. Digital Communications and IT Infrastructure

Event data are acquired as a 12 bit value representing the integrated charge of each event detected by the system. On this particular system 10 bits were considered good enough for histogram generation, so only the 10 most significant bits were stored and the other 2 were discarded as the first data processing stage.

The histogram is stored as an array of integer 32, so 4 bytes will be used to represent

each of the channels on the histogram, this will give us a maximum of 4.294.967.296 events for a single channel. As said before the histogram represents only the 10 most significant bits, giving us a total of 1024 channels, so we can find the total histogram size to be $1024 \times 4 \text{ bytes} = 4 \text{ KB}$.

The system is expected to generate a maximum of 51 full histograms: the total accumulated histogram(1), the hourly accumulated histogram(24), histograms for each minute of the last 15 minutes (15), histograms accumulated every 10 seconds over the last minute(6) and the histograms accumulated every 2 seconds over the last 10 seconds. These histograms are stored internally and numbered 1 to 51 for identification purposes. The system can also implement simpler storing schemes like keeping only a total accumulated histogram, the histogram over the last hour and the histogram over the last 5 minutes, different combinations are possible.

Histograms are sent to the Wireless Gateway devices with the following format,

Header	Clock	Histogram	Localization	Packet End
1 Byte	4 Bytes	4 KB	5 Bytes	1 Byte

Fig. 3.9. Data packet format

Histogram data is stored locally on a uSD card in FAT32 format, connected to the microprocessor using an extension module for the Arduino Mega board controlled via a SPI interface. This is done to ensure data is not lost if batteries were depleted while the personal dosimeter is running. Local storage can also be used to keep storing data if communication with the wireless gateway is lost, if this were to happen once communication is regained unsent packages will be sent to the wireless gateway. Using a 2 GB microSD card the system can store more than 1 million histograms, meaning that if the batteries allow it, the system could store data of up to 24 days of continuous operation.

Time stamping is achieved using a real time clock module (RTC - DS3234 - Maxim Integrated) connected to the main processor through a SPI interface. This clock module contains a battery that it can use if power from the main system were running low thus not losing its time stamping capabilities even if the main batteries of the system were depleted.

Data is sent to the Wireless Gateway using a Bluetooth module (WT12, Bluegiga), packets can be sent in less than 300 ms. Bluetooth communication can give us a data rate of up to 2 Mbps, which is good enough for this application. Other communication options like WiFi or 3G were discarded mostly due to the increase in power consumption although they could connect the personal dosimeter directly to the internet allowing us to remove the Wireless Gateway from the current architecture in scenarios where indoors localization is not needed.

The Wireless Gateway is implemented using a Raspberry Pi with an ARM 11 pro-

cessor running the Raspbian OS. Bluetooth USB dongles are connected to this device so that it can communicate with the personal dosimeters. The Bluetooth adapters support BT2.1+EDR allowing a maximum data rate of 3 Mbps and 100 meters of coverage (line of sight, LOS). The Raspberry will be connected to the internet allowing it to communicate with the Central Processing System.

The Central Processing System is an Apache Tomcat running on an Ubuntu Server OS connected to a MySQL database. A web interface developed using Java runs on the server accessing the database where the dosimetry data is stored.

The web app includes user logins and different user profiles enabling access control and data access restriction. Using this interface users can communicate with the dosimeters and check in real time the latest measurements for each of the dosimeters on the field. The system is designed to allow to send configuration information as well as alarms to the dosimeters from the Central Processing system, however this function has not yet been implemented.

3.3.3. Signal Processing and Data Acquisition Electronics

On previous implementations fast scintillation crystals were considered, thus it was mandatory to use a FPGA to control the data acquisition. This also imposed the use of some signal processing elements like a baseline restoration block. However since finally the crystal to be used was a CsI crystal with decay times close to $1\mu s$ it was now possible to redesign the control logic so that it could be achieved using only the microprocessor and not requiring a FPGA.

The first step on the analog signal processing chain is to amplify signals coming from each channel individually adding a first order low pass filter to remove high frequency components ($>100\text{MHz}$). Since our goal is to acquire only energy information, and not event localization, the 4 signals coming from the SiPM were summed together and then sent to both the integration stage and the comparator. The opamp chosen for both the summing stage and the amplification stage was a THS4062, a 180 MHz high speed dual amplifier from Texas Instruments.

A high speed comparator (ADCMP600 - Analog Devices), was used for valid event detection, this system will trigger if the pulse were to fall below a certain threshold. Threshold values were adjusted using a potentiometer on the board. The threshold value used had great influence on the acquired histogram, using a too low value will result on many noise events being acquired thus saturating quickly the low channels of the histogram, while a high value can make us loose the low energy events, thus reducing the sensitive range of the dosimeter. This digital signal is also sent to the microcontroller allowing it to know that a new event has been acquired, so that it can start the ADC conversion once the integration time has elapsed.

Fig. 3.10. Signal Conditioning and comparator stage

The comparator output is connected to a digital latch (SN74LS279AD - Texas Instruments) this latch is part of the new architecture used to replace the FPGA. The latch will make sure that the integration gate is opened as soon as possible (< 50 ns) and it remains so until the data conversion has finalized at which point the latch is reset by the microcontroller.

The analog signal going to the integrator is delayed 50ns using an analog delay, this ensures that the delay introduced by the comparator and the latch does not make us lose the rising edge of the radiation pulse coming from the detector. Once the signal is received from the latch, the integrator starts integrating the radiation pulse on a capacitor. The integration is ended by the microcontroller and the capacitor is discharged by closing the gate.

The final stage on the analog chain is the ADC, in this case a LTC1415 12 bits@1MSPS ADC from Analog Devices is employed. Conversion is started once the signal is received from the Arduino. This ADC has a data conversion signal that will indicate when the ADC has finished and the data can be read. Data is read using a parallel interface, thus 12 pins are needed for the data read out. Once the conversion has finished and the data has been read the microcontroller will reset the latch, closing the integration gate and preparing the system for the acquisition of a new event.

Fig. 3.11. Dosimeter Electronics Scheme

Pile-up events can be discarded if a new pulse is received from the ADC during the conversion phase. However if the new event arrives before the previous one falls below the threshold set on the comparator, the pile up will not be detected. However in a system like this we do not expect to see a significant rate of pile-up events.

This new electronics configuration allows us to get rid of the FPGA in the data acquisition chain, thus greatly simplifying the system and reducing its size and power consumption, both very important factors for a device that is intended to be worn by the user running on batteries. While implementing the system we considered getting rid of the external ADC and using the ADC in the Arduino, but this ADC was too slow and the analog signal was degraded during the conversion process giving very noisy histograms.

The group at URJC developed a power distribution board, able to provide all the voltages needed to make the system work including the high voltage $>+70\text{V}$ needed to make the SiPM work. This board included as well a battery management circuit handling battery state and charges when needed. The high voltage power supply (SIP90 - Emco) was used along with a programmable digital potentiometer, for small adjustments of the high voltage values allowing us to compensate gain variations due to temperature changes on the SiPM; for this purpose a small temperature sensor was placed on the analog processing board just below the SiPM.

3.3.4. Testing the System

Several integration tests were designed and carried out between the different elements of the system.

Event acquisition and local histogram was tested by sending the data out of the USB port on the Arduino and by reading the histograms stored on the microSD card when it was connected.

Several radiation isotopes were used to ensure that the system could detect events from 50 keV to 2 MeV. These tests served as well to determine the proper settings for the threshold potentiometer.

Fig. 3.12. Spectra acquired proving the range of the detector

On the spectra acquired during testing we saw that there was some noise due to coupling of signals to the parallel lines of the ADC output. For this reason we decided to try a new ADC (ADS8329 - Texas Instruments) that used SPI communications instead of a parallel output. There were other advantages to using this new ADC, it had a smaller footprint and 16 bits of resolution.

Fig. 3.13. Comparing the spectra obtained with different ADCs

Finally a complete integration test was realized comprising the personal dosimeter unit, the wireless gateway and the central processing system. Below we can see a result of said tests.

Fig. 3.14. Outputs of the central processing system during a test at URJC

3.4. Latest Working Prototype

The prototype presented on the previous section is good enough as a proof of concept design however it was too bulky and comprised of many components that could be found integrated on some of the new microcontrollers. Arduino is good enough for a test system, but it can not be used on commercial products specially if one is aiming at reduced size and power consumption.

With this idea in mind we started to work on an improved design that could improve the previous one while maintaining the same functionality since a company had approached to us and asked if we could provide something more *market ready*.

3.4.1. Detector

Some time had already passed since we started working on the dosimeter, during this time the manufacturer of the SiPM array used on the prototype had released a new generation of SiPM sensors.

We found one sensor similar in size and characteristics to the one we had used before, and so we chose to use the detector model S12573-050C. It has an improved gain and fill

factor. It also has less dark counts than the previous family of detectors as well as a lower operating voltage.

Parameter	S12573
Number of channels	4(2x2)
Effective Area	3x3 mm
Number of pixels/channel	3600
Pixel Size	50x50 μm
Peak Sensitivity	450 nm
Operating Voltage	65 $\pm$ 10V
Gain	1.25x10 ⁶

Table 3.2. S12573 specification

Along with this new family of SiPM the manufacturer had released as well a compact high voltage power supply C11204, that included built in temperature gain correction for the SiPM sensor. We used this new power supply on our system thus eliminating the need of implementing the control ourselves and reducing the chances of a possible error due to a misconfiguration of the gain control loop.

3.4.2. Analog read out electronics

The analog signal chain was kept very similar to the one used before. Some of the changes were, the comparator used was replaced by a model TLV3501 (Texas Instruments) that had better timing than the one used on the first prototype.

The analog delay element used was replaced by one with a smaller footprint, to help achieve our goal of making the system as compact as possible. We considered eliminating the delay, but losing even a small part of the rising edge of the radiation pulse from the detector had very bad effects on the obtained histograms.

The major change on the analog side was that we got rid of the ADC by using the ADC integrated on the microcontroller. The internal ADC has a sampling time of 1Msps with a resolution of 16 bits, and since it is already on the microcontroller, there is no need to add any more signal lines, thus reducing the required PCB routing space. On the previous design we needed 12 lines for the readout since it was a parallel ADC.

Title: CSN Detector V5		* LIM-HGGM	
Size: A4	Number: 1	Revision:	RCP
Date: 08/04/2019	Time: 18:32:59	Sheet: 1 of 2	
File: D:\Transfer_Rao\CSN documents\Circuit_Basic\CSN_v5.Acond_Elec_Sch.Dwg			

Altium

Fig. 3.15. Signal conditioning electronics 1/2

Title: CSN Detector V5		* LM-HGGM	
Size: A4	Number: 1	Revision: 1	Rev: 1
Date: 08/04/2019	Time: 18:32:59	Sheet: 2 of 2	RCP
File: D:\Transfert_Rao\CSN documents\Circuitos_Rao\CSN v51\analog ADC SchDoc

Fig. 3.16. Signal conditioning electronics 2/2

3.4.3. Communication and peripherals

This is the part that has suffered the most changes when compared with the previous design.

The first and most important change was to replace the ATmega microcontroller and the Arduino board by a TM4C123 ARM microcontroller from Texas Instruments. This microcontroller not only allowed us to get rid of the external ADC as was discussed before, but it also includes some internal features like a Real Time Clock module.

This internal real time clock module allows us to get rid of one more element on the system, with the corresponding improvements on size and consumption.

Since we had already seen that there was no optimal configuration when it came to the digital communications part, we decided to go for a modular approach, which is fairly common on wearable devices.

We used the communication ports available on the microcontroller to allow connection to different communication devices. This way small communication boards can be connected to the main board that includes the analog readout, the detector, power supply elements and the microcontroller.

Now, we can tune the device to different options and if something is not needed we don't connect it and thus save the power required for using it. Communications modules can include WiFi, 3G, Bluetooth, ZigBee, etc. On this new design we can even combine several communication protocols at the same time if needed.

Fig. 3.17. System Prototype, modular design

Another option added by using this new microcontroller was the option to connect the personal dosimeter to a phone using the built in USB device peripheral on the microcontroller. Connecting the device to a mobile phone will allow us to remove the batteries

since the device could be powered by the phone over the USB. It also allow us to use all the communication and localization elements on the phone, thus reducing the functionality of the dosimeter to radiation event detection and histogram generation. If the system is to be used like this no external modules might be needed since we can use the phone for accessing the internet and sending the data acquired by the dosimeter.

There were no changes performed on either the Wireless Gateway or the Central Processing System. However with the new possible architectures there is little need for the Wireless Gateway, except for the scenarios including indoor localization.

Fig. 3.18. Latest working prototype

3.4.4. Testing the system

We tested the acquisition of radiation histograms on this new system, below we can see the obtained histograms.

Fig. 3.19. Spectrum for ^{22}Na and ^{137}Cs

As can be seen in figure 3.19, there is an improvement on the acquired histograms in part due to the use of a better ADC and using interpolation for the histogram gener-

ation instead of just dismissing the least significant bits when going for a 1024 channel histogram.

Integration tests with the Wireless Gateway and the Central Processing System were not finally performed since the company interested on this dosimeter lost interest in it and thus the communication modules for this new design were not built.

4. SIPM BASED SMALL ANIMAL PET RING PROTOTYPE

This chapter is dedicated to a PET detector for small animals built using SiPM detectors. Along this chapter we discuss the different concepts evaluated to select a final SiPM detector configuration to be used.

Previous experience in working with PMT designs defined the starting point for the SiPM based detectors. The first step in this direction was to test if the charge distribution schemes used with PMTs was valid for SiPMs. For this purpose we built a first simple prototype using only two detectors. This work was presented in San Diego at the IEEE NSS-MIC conference of 2015 [47].

Fig. 4.1. Flood field and image of the detector presented at the NSS/MIC conference of 2015

In a second approximation we moved on to a detector configuration quite similar to the final design presented in this chapter. This design was presented in Strasbourg at the IEEE NSS-MIC conference of 2016 [48].

Fig. 4.2. Flood field and image of the detector presented at the NSS/MIC conference of 2016

The PET system proposed in this chapter consists of eight detectors disposed in a ring configuration. The ring inner diameter is approximately 80 mm, a wider ring could be possible if we increase the number of detectors used. The ring as well as the housing for the detectors are built using 3D printed parts.

Each detector is comprised of four SiPM sensors, model S12642 by Hamamatsu arranged as a 2x2 matrix of SiPMs. Each of the sensors has a sensitive area of $13 \times 13 \text{ mm}^2$, giving a total sensitive area per detector of $26 \times 26 \text{ mm}^2$. Coupled to the SiPMs is a LYSO crystal array of 17×17 pixels of $1.3 \times 1.3 \text{ mm}^2$, the width of the reflector covering the pixels is 0.8 mm giving a pixel pitch of 1.38 mm. This array has a thickness of 12 mm. The crystal array is coupled to the SiPMs using an index of refraction matching silicon grease, BC-630.

Tests of this system were carried out using a robot built to move a point source around creating different shapes in space. Results of said tests are presented at the end of this chapter.

4.1. PET detector electronics

In this section we will discuss the different elements that constitute a PET detector. Most SiPM based PET detectors can be divided in the following stages:

- **SiPM biasing** : This part handles the filtering of the high voltage applied to the SiPM, as well as the selection of a proper biasing element that will directly affect the amplitude and shape of the pulses obtained from the detector.
- **Charge Multiplexing**: This involves the electronics used to distribute the charge along the circuit, reducing the number of analog outputs needed to obtain the position, energy and timing information. The main goal of this element is to reduce the

number of output channels as much as possible while preserving position, energy and timing information.

- **Active Stage :** In this last part is where the signal is adapted to the input range of the data acquisition system being used. Some other signal processing techniques can be used if needed, like filtering, baseline restoration, etc, in order to improve the SNR of the system.

The electronics in the detector play a very decisive role, and each element along the signal conditioning chain has a great impact on the overall image quality. A mistake in any of the points along the signal chain can be carried over and become very difficult to find.

There are many other possible detector configuration options, that differ from the one previously presented, like using an ASIC for the front-end electronics, up to using an ASIC for both the electronics and the data acquisition part.

Another solution could be to amplify and acquire each SiPM channel individually. This can be done for small detectors in a lab, but this solution does not prove very useful when working with a whole PET scanner as the number of ADC channels needed would increase considerably making the system impractical.

4.1.1. SiPM Biasing

One of the first issues to consider when working with SiPMs, as opposed to PMTs, is the fact that they support different polarities, while PMTs needed always a high negative voltage. SiPMs can be used with both positive and negative voltages, it is just a matter of choice[49]. It is common that some manufacturers tend to always recommend a certain polarity on their devices.

The first element of our front end electronics is the biasing circuit. This circuit is quite similar for most SiPM devices currently on the market, but it can be different depending on the model. For example, the new families of Sensl detectors come with a fast output, that is very useful to improve the timing performance of the detectors, and a standard output quite similar to the one on most devices. The fact that this devices have different outputs with different dynamic responses means that special care must be taken when working with them.

In our case since we use Hamamatsu detectors, the recommended biasing circuit is the one pictured below, which is the one we use.

Fig. 4.3. SiPM bias circuit used on our detectors

On this very simple circuit is very important to point out that both capacitors should withstand up to 100 V. The new family of SiPMs detectors from Hamamatsu works around 55 V, but the previous ones work around 70 V. Another interesting element is the limiting resistor, used to ensure that the current going through the SiPM is always in an acceptable range.

The selection of a proper biasing resistor is not a trivial matter, the most common value is to use 50 Ω , higher values can be used to obtain larger pulses at the cost of sacrificing timing. Another option is to use a capacitor connected to the detector along with the biasing resistor to improve the timing of the detector. On [49] there is a very detailed explanation on how the different biasing circuits work and what are the pros and cons.

We chose a simple positive polarity with a 50 Ω biasing resistor since it is the one that suits better to our needs. The selection of this resistor is influenced from several factors like the multiplexing scheme to be used and the timing requirements of our system. Due to the fact that modifying this value can give pulses of different amplitudes, it will also affect the selection of the amplifiers used on our boards.

One very important aspect when working with SiPMs is the overvoltage to be used. This overvoltage is the voltage level above the breakdown voltage of the SiPM. When working with different SiPMs is better to speak about overvoltage, since different SiPMs

can have very different breakdown voltages. Sensl devices typically have a breakdown voltage around 30V, as well as the ones produced by AdvanSiD. However, Hamamatsu detectors are around 55V or 70V for the older families. Devices with different breakdown voltages working at the same overvoltage should behave similar.

$$V_{ov} = V_{op} - V_{br}$$

There is a direct relationship between the overvoltage used and the gain of the detector, so one might consider that is better to use a very high overvoltage value. However, there is a big drawback to this and is that it also increases the amount of dark counts. Dark counts are an undesired defect present on SiPMs and APDs [50], so basically by increasing the overvoltage we can end up making our sensor a lot more noisier, thus degrading the SNR.

Timing is also affected by the overvoltage value in use as it directly affects the PDE of the detector and, in turn, the coincidence time resolution (CTR) [51]. Increasing the device sensitivity, increases the chances of detecting a photon as soon as it arrives at the surface of the detector. But going back to the increase in dark counts, attempting to perform timing measurements on a noisy detector can produce a large number of false trigger events that have to be discarded later on either by energy thresholding or by coincidence detection. Energy thresholding is preferred to coincidence detection, because it can generally be performed on the detector level, while on the coincidence level we will have to acquire and process unwanted events. As the number of this unwanted events increases it might prove difficult to cope with the high data throughput of the system.

Generally, manufacturers indicate on the datasheet of the SiPM the recommended operating voltage to use. One thing to notice about SiPMs is that not all channels on a detector will have the same breakdown voltage. It is better to always be on a safe zone where we can guarantee that all channels on the detector are working on Geiger mode. If we were to be below this value on a specific channel we will only be able to detect very high energy events on said channel.

■ TEST DATA

		Ta = 25°C							
Serial No.	188		189		190		191		
Element No.	Vop (V)	dark @Vop (uA)	Vop (V)	dark @Vop (uA)	Vop (V)	dark @Vop (uA)	Vop (V)	dark @Vop (uA)	
D4	66,70	0,37	66,61	0,38	66,68	0,56	66,65	0,38	
D3	66,69	0,38	66,66	0,39	66,69	0,56	66,65	0,39	
D2	66,70	0,37	66,68	0,47	66,68	0,53	66,63	0,40	
D1	66,70	0,34	66,64	0,57	66,66	0,52	66,64	0,41	
C4	66,75	0,35	66,61	0,38	66,69	0,57	66,64	0,36	
C3	66,72	0,38	66,64	0,40	66,64	0,56	66,62	0,36	
C2	66,75	0,36	66,64	0,39	66,62	0,56	66,60	0,37	
C1	66,68	0,38	66,62	0,34	66,61	0,50	66,60	0,38	
B4	66,70	0,37	66,66	0,32	66,61	0,50	66,64	0,35	
B3	66,74	0,39	66,60	0,30	66,59	0,53	66,62	0,36	
B2	66,77	0,38	66,62	0,30	66,64	0,54	66,59	0,36	
B1	66,75	0,37	66,64	0,32	66,67	0,55	66,64	0,40	
A4	66,66	0,45	66,59	0,32	66,61	0,49	66,63	0,34	
A3	66,73	0,40	66,68	0,32	66,61	0,49	66,67	0,33	
A2	66,74	0,38	66,65	0,34	66,62	0,52	66,65	0,34	
A1	66,72	0,39	66,63	0,33	66,62	0,49	66,65	0,34	

Vop : Recommended operation bias voltage for each elements.

We estimated the gain at Vop as $M = 1.25 \times 10^6$.

Fig. 4.4. Recommended operating voltages provided by Hamamatsu

4.1.2. Multiplexing Network

The most commonly used multiplexing network in radiation detectors is the one designed by H.O. Anger in the sixties[52] . It is a charge multiplexing network that distributes the charges in the network resulting in only four analog outputs.

Fig. 4.5. Charge distribution network

We have used this network as well, but in our experience it can induce some negative effects due to the coupling of neighbouring pixels when too much current is drawn from a specific point in the network. When a high energy event is detected, we can see a small up swing on the signal level and this is noticeable on the signals we get at the corner outputs of the network. This undesirable effect degrades our SNR and affects our image quality. The effect could be compensated by properly tuning the values of the resistors used on the network to minimize the coupling.

Another problem of this network is that there is a significant change in gain for the pixels closer to the corner when compared to those in the center of the matrix, this produces a common effect known as pin cushion effect. We can see below, figure 4.6, how this creates a sort of bent image on the sides. Some groups have came up with ways to solve this problem by using data processing or simply by using a different equation for finding the pixel position[53].

Fig. 4.6. Pin Cushion effect using the network shown in figure 4.5

There are different ways of implementing an Anger multiplexing scheme, some use only capacitors and no biasing resistor for each pixel, others use resistors instead of capacitors, and some others use the network along with a biasing resistor[54],[55]. In our experience all of these solutions suffer from the two problems stated above. The best results, however, are obtained when using a biasing resistor along with the charge distribution network[56],[57].

The multiplexing solution we consider the best option is the one proposed by Popov[58]. This solution is also commonly known as rows and columns distribution. In this case, a biasing resistor is used for each pixel along with two more resistors, one for each of the coordinate axes (columns and rows). When working with this configuration care has to be taken to avoid the same negative effects that we saw when using the Anger distribution. To avoid it, we must use an impedance with enough resistance to minimize the coupling of the network elements.

Fig. 4.7. Row and columns charge distribution network

There are some other solutions used for detecting the position of the radiation event apart from the charge distribution network[59],[60]. These are great technical solutions, however they prove quite challenging to scale up as they do not offer a level of multiplexing as high as the methods presented before.

As it was discussed before, another possible solution is to use an ASIC instead of using good old analog electronics. There have been proposed several designs like [61],[62]. However, they require a great degree of tuning along with heat dissipation elements as well. ASICs are clearly the future of compact, highly efficient electronics and as time goes on, we will see them integrated in more and more designs, but the ones available right now are not the optimal solution for cases like ours.

One of the most difficult design choices is to decide whether to use a high level of multiplexing, digitizing as few signals as possible, or on the contrary dismiss most of the analog processing and digitize as many channels as possible and as close to the detector as possible. There is no clear answer to this, it highly depends on the kind of system being built and what are the expected results. We consider that for systems like PET imaging devices, where the data acquisition system tends to be quite large, expensive and consume lots of power, it might be better to use as much multiplexing as possible, minimizing the number of analog output channels and the amount of digital information that needs to be handled by the system. A different and not so distant option will be to design a system running entirely on ASICs that could digitize the signals from each SiPM channel while keeping power consumption and size at a minimum. This might be the future for PET

detector electronics, but most of the ASICs currently available on the market are not quite there yet.

4.1.3. Active Stage

The final stage in our analog signal chain is the one in which we include amplifiers. We do it this way, so high up on the signal processing chain, to reduce the amount of amplifiers needed to a minimum. This reduction in the number of amplifiers has a great impact in the overall performance of the system. It not only reduces power consumption, with all the advantages this implies, but also has an impact on the cost per detector of our system. One more consideration is that if at any point we were to try and use this system inside an MRI scanner, having the less active components possible will make our system more resilient to perturbations from the MRI.

In radiation detectors probably the most common configuration implies a transimpedance amplifier connected directly to the detector. This proves to be good configuration when testing and characterizing individual pixels, but is not optimal when working with several pixels at the same time. Also transimpedance amplifiers have more stability issues than voltage feedback amplifiers [63]. In the past, transimpedance amplifiers[64] were preferred to voltage feedback amplifiers due to their high input impedance and their higher bandwidth, but at the moment there are voltage feedback amplifiers with a large enough bandwidth to work with radiation pulses[65].

There are also some groups using wideband amplifiers with high dynamic range in their experiments [66]. In this case they use MAR-6+ amplifiers from Mini-Circuits. These amplifiers offer a very good SNR and present a larger bandwidth than most common op-amps, but they also require more power, making heat dissipation a real concern on detectors using this kind of amplifiers.

We had used in the past the THS4032 voltage feedback amplifier, from Texas Instruments(TI), and they were very well suited for PMT signals. We tested them with SiPMs and the results were also quite good. However, we switched to a new opamp the OPA2690 from TI since it has a larger bandwidth and a better slew rate. Another very interesting aspect of these amplifiers is that they can work with smaller power supply voltages, making it feasible to work at ± 3 , or ± 1.8 V, adjusting to the new trends in electronics of using always smaller voltages to reduce power consumption and allow for higher bandwidth on the digital domain.

With this amplifier we perform a weighted sum of all the signals coming from the charge distribution network. This gives us the position information about where in our network did the event occurred. We are also performing multiplexing in this stage by doing this weighted sum going from sixteen input position signals to only four outputs. The equation for finding the positions after the network is:

$$X = \frac{X_+ - X_-}{X_+ + X_-} \quad Y = \frac{Y_+ - Y_-}{Y_+ + Y_-}$$

For the last stage we use a configuration that allows us to modify the signal polarity and amplitude according to the needs of the data acquisition system. This stage implements a Sallen-Key filter in the event that the signal is very noisy, or it can be used only to adjust the signal range.

Fig. 4.8. Weighted sum and filtering stages

In our current detectors the signal is clean enough that we do not need to use any filtering, so in this final stage we only amplify our signal to optimize the dynamic range of the analog to digital converters of the data acquisition system.

4.2. Power distribution board

As we mentioned earlier, SiPMs require high voltages which, even if they are not the 1000V needed for PMTs, are still quite high, high enough that it is not easy to find power supplies for these values. Also, SiPMs draw very little current, in the order of μA depending mostly on the amount of detector cells that fire for each radiation event stopped by the scintillation crystal. Smaller crystals, like pixelated matrices, provide less light and thus draw less current, while larger monolithic crystals provide more light and draw more current.

When working with these detectors we considered using the following two different power supplies the SIP90 from EMCO and the C11204-01 from Hamamatsu:

Parameter	SIP90	C11204
Output voltage (VDC)	25-90	50-90
Max Output current (mA)	1	2
Output Ripple (mV)	0.5	0.1
Output Programming	Analog	Digital(UART)
Temperature Compensations	No	Yes

Table 4.1. SiPM Power supply comparison

The power supply from Hamamatsu offers superior performance when compared with the one provided by EMCO. An aspect that could be argued is the fact that the power supply from Hamamatsu can only be programmed using a serial interface whereas the one provided by EMCO can be controlled using a simple potentiometer. The problem with using a potentiometer for power supply adjustment is that it can degrade over time thus modifying the gain of our detector. A power supply controlled using a digital interface does not suffer from this effect and will enable remote control (very useful for calibration) although it will require to allocate a communication port to program it.

A very relevant aspect of the one developed by Hamamatsu is that it includes a temperature compensation functionality. Although some of the new families of SiPM are not so affected by temperature changes, it is recommended to include some kind of temperature compensation[67], specially if these devices are meant to be operated for long periods of time, like is the case for PET imaging systems. Since the gain is affected by both the overvoltage and the temperature, small changes in the overvoltage value being used can help us compensate for the drift in temperature. We are actually not adjusting the overvoltage over time, but rather it is the breakdown voltage of the devices which changes with temperature[68] and we compensate for this change, which is why with this increases/decreases on the applied voltage we see none of the negative effect that we mentioned before.

Gain non-uniformity among cells is always present on SiPM detectors, and even though manufacturers fight very hard to reduce them as much as possible, they are still present on the detectors. Sensl claims that their devices present such a good output uniformity that they can all be supplied with the same voltage[69], but this is not the case for Hamamatsu. When acquiring a new detector from Hamamatsu, a spreadsheet is provided with the breakdown voltages for each of the pixels on the detector. As can be seen on figure 4.4, the difference in a single SiPM detector array is not so much, while the difference with another detector array can be high enough as to affect detector performance if

both detectors were to be supplied with the same voltage. Even if we manage to use the same voltage on some of the detectors, we will still have differences in the gain of each of them. This is not only influenced by the SiPM sensor, but from the whole signal chain, including the front-end circuit and the data acquisition system. So we consider it a good idea to have a way of making very small adjustments to the gain on each detector.

With all of this in mind, we designed a power distribution board that can host up to 4 C11204 power supplies, and we verified that one of these power supplies can power up to eight SiPMs, which in our system translates to two PET detectors. If we power the two detectors closer to one another the chances of both detecting a high energy event simultaneously are very small, so one power supply should be enough to power them. We tested this in the lab with two detectors in coincidence and found that the power supplies had no trouble dealing with eight SiPMs facing one another.

The power distribution board is controlled with a TI Launchpad microprocessor board that can handle the communication with the four power supplies simultaneously and connect to a PC or another device using USB or serial communications. Using this, we can create a closed loop to adjust the gain in our detectors. We can acquire an energy spectrum, find the value of the 511 keV peak and adjust the high voltage of the detector accordingly, until all detectors outputs are in the same voltage range.

Fig. 4.9. Power distribution board

4.3. Acquisition System

The acquisition system used on this imaging device is a Nutaq PicoDigitizer 125 capable of acquiring up to 32 analog inputs simultaneously per module [70]. This is a real time data acquisition system capable of sampling the pulses from a radiation detector. This system will be further described later on.

A charge integration acquisition system will also be presented since it is worth considering how this system works in comparison with the real time acquisition system we use. We will see that there are some obvious advantages to the use of a real time acquisition system. However, the image quality obtained from a charge integration system is also good, proving it can be a good contestant for a real time acquisition system.

4.3.1. Charge Integration Data Acquisition System

The first data acquisition system we used was one previously developed at our group for the characterization of individual detectors. It has five input channels since this is the number of outputs from previous PMT based detectors developed at our group, four position outputs and one energy output. This acquisition system is quite similar to the one described before in the previous chapter 3, in fact it was the one used as starting point for that acquisition system. The first stage on this system is an amplification stage to adapt the input signal to our desired range.

In this system, one of the signals has a different data path. The energy signal is the one used for event detection and timing measurement. This signal is split into two at the input and one of the new signals will be heavily amplified to be later on compared to a reference threshold voltage.

The output from this comparator stage is what will give us event detection and timing information. This digital signal will be connected to a Cyclone 2 FPGA available on the system, that acts as acquisition control and data communication element.

The position input signals and the energy signal all follow the same signal conditioning path, they are amplified and later sent through an analog delay line. This delay line is used to compensate for the delay in the comparator and the reply from the FPGA to activate the integration gate.

Next part is the integration stage, in it there is a switch used to control the integration. During normal operation, when an event is detected, the FPGA signals the switch to open and start the integration procedure, after a given integration time have elapsed the FPGA will signal the ADCs to start conversion.

This acquisition system uses four ADCs (LTC1415) with very low power consumption, 12 bit resolution at 1 MSPs, the most important characteristic of this ADCs is that they are able to start the conversion on demand. This not only saves power, but also gives us more precise control over the signal integration time. This integration time will depend

on the detectors being used, SiPM vs PMT, the front-end electronics employed (sometimes a RC shaper network is used on radiation detectors to modify the pulse shape), the scintillator being used, some scintillators are faster than others, etc. So the selection of a precise integration time for each detector being tested is a very important factor.

Once the conversion is finished, the FPGA closes the integration gate, discharging the integration capacitor and preparing the system for the acquisition of a new event. If a new radiation pulse were to be detected during the acquisition process the event being acquired will be discarded and considered a pile-up event. The limit on the maximum number of events that can be acquired per second on this system is not imposed by the conversion time as might be expected, but by the communication interface used.

Data is stored in the FPGA, as follows:

- 32 bit timestamp
- 5x16 bit position and energy information

This gives us a total of 14 bytes per event. This board does not have a RAM module, only the FPGA RAM is available which is very limited (239616 bits maximum [71]) so for a practical design we will use at most 15.000 bytes giving us an event memory buffer with a depth of 1000 events. We can increase this figure but it will use up almost all of the FPGA memory resources and still not give us a great improvement, as will be seen below the bottleneck on this system is the communication speed.

The most problematic part of this design is that the communication method used is a serial port connected through a USB interface giving a maximum communication speed of 115200 bps, so for a buffer of 1000 events it takes around 1 second to transmit the data. We could keep on acquiring events while sending the data to the PC, but since we normally expect event rates well above 1 Kevents per second, there is no need to do that. Also, there is no point in using a larger event buffer in the FPGA since it will take twice that time to empty it. Thus, we can state that the maximum event acquisition rate of this system is around 1 Kevents/second, this can be used for detector characterization but not for an actual PET imaging system.

However, we would like to point out that the reason for this system having such a low maximum event acquisition rate is due in this case to the communication and in second stance to the small available memory on board. In a design using an onboard RAM memory and a faster communication link, like gigabit ethernet, the limit will be imposed by the conversion time plus the integration time giving us roughly 1 Mevent/second, the main limitation in this case will be imposed by the conversion rate of the ADC, using a faster ADC will bring us closer to a real time data acquisition system. The main advantage of this system compared to a real time acquisition system is that it requires no digital data processing, the amount of stored data is rather small and the power consumption per channel is reduced by a factor of 10 (PicoDigitizer 125/16 consumption is 35W according to its User Guide).

4.3.2. Real Time Data Acquisition System

This prototype uses a commercial data acquisition system, a Nutaq PicoDigitizer 125[70]. This system gives us 32 analog input channels and what really makes it a good option for a PET data acquisition system, it includes a Virtex-6 SX315T FPGA that can be programmed by the user thus allowing us to tune the real time data acquisition blocks inside the FPGA and transforming this commercial system into a PET data acquisition system. We have developed VHDL IP cores that are integrated in the data flow used by the PicoDigitizer, this system uses two of such IP cores.

The first IP core handles event detection, for that purpose it includes a configurable trigger and offset subtraction, using it we can adjust independently the offset and threshold levels not only for each detector, but for each channel on each detector, giving us a finer tuning of the event detection part. This IP core will generate a trigger pulse whenever an event is detected according to the configured threshold, it can work with pulses from both polarities.

The second IP core is an acquisition control IP, it handles coincidence detection, acquisition mode selection and event storage. Since we are running the system at the maximum sampling speed of 125 MHz we can consider that if there is a coincidence event we will detect two pulses coming from the event detection cores with at most 1 clock cycle of difference. This is used to find coarse coincidences, apart from this, there is a header included in the data for each event that includes a fine timing value coming from TDCs in the system. Currently, we are not using this fine timing values, since we are using the system with low activity levels for the characterization and thus the amount of random coincidences is very low, but in the future a comparison stage will be added to obtain the fine timing values since the PicoDigitizer includes as well LVDS digital inputs that can be used to trigger the TDCs in the system.

The acquisition control IP core supports different acquisition modes.

- **Offset acquisition mode** in which whatever comes in is stored, this is more or less the normal functioning of the PicoDigitizer, and is useful to acquire the offset for each channel prior to start working with the system.
- **Raw event storage mode**, in this mode events are sampled and each sample point is stored and transferred to the computer. This mode is very useful for detector characterization, or if we want to do some advance data processing with the incoming pulses, for example fine timing algorithms can be used on the edge of the incoming pulses. The main disadvantage of using this mode is that since the amount of data transferred to the PC will be larger, the dead time when transferring the data increases and the amount of data to be processed increases as well, increasing the computational load on the acquisition PC.
- **Signal Integration mode**, the pulses are integrated digitally inside the FPGA using

the pulse samples and a single value is stored for each detector channel, thus greatly reducing the amount of information that needs to be send to the PC. This is the mode we commonly use when characterizing the whole system. On this integration mode we can choose the integration interval to be used.

Depending on the mode selected, data is stored in a different way on the memory of the system. When using the offset mode, we will have a bunch of data samples without taking into account any trigger. On the raw event mode, for each detected event we will first have a header with the timing and trigger information. After the header all data samples comprising the event will be stored, for that we can choose how long will our pulses be, and how many values before we detected the event do we want to store, only the values from detectors on which a pulse was detected will be stored. On the integration mode, each event will have a header like in the previous mode and only one value for each channel of each detector on which a trigger has been detected.

We store only those values on which there is a trigger event to store less values and to also overcome a limitation of the data acquisition system. When using the 32 channels as inputs, The PicoDigitizer 125 allows only a maximum sampling frequency of 75 MHz, but this limitation comes from the amount of data that can be transferred to the RAM memory on the system, so by sending only the necessary information we could store coincidence events for up to 4 detectors at the same time allowing us to use the full 32 analog input channels.

To ensure that our system was working properly we compared the results obtained using the raw data acquisition mode and the integration mode.

4.4. Detector description

The detectors are comprised of a 2x2 array of SiPMs, a very common and useful configuration. This configuration is compatible in size with detectors using the previous R8900 PMT, allowing us to reuse some mechanical components if needed. The SiPMs are S12642 from Hamamatsu, we have also tested this system using the new S13360 family and the results obtained are quite similar, so we decided to use the older models since we already had them in the lab. Each SiPM has 16 channels arranged in a 4x4 matrix, giving us a total of 64 channels arranged in an 8x8 squared matrix.

In each detector there are two electronic stages. The first stage is a passive charge distribution network that uses a row and columns scheme, thus reducing the amount of analog signals from 64 to 16, 8 X signals and 8 Y signals, a high value resistor has been used on the network in order to minimize the interaction between neighbouring pixels. We checked that if smaller resistor values were used the interaction between elements on the network was too high and this had a great impact in the overall SNR. The second stage takes as input all these analog signals sums together the signals from each direction and gives them the proper amplitude to be used with our acquisition system. This second stage

is an active amplification stage and includes four dual operational amplifiers, used for the summing and conditioning of the analog signals. The output from this second stage are the four analog signals that we use to acquire the position information in our detector X+, X-, Y+, Y-.

Fig. 4.10. Two fully assembled detectors and two detector cases

4.5. Prototype Design

We decided to go with a conventional ring structure, for that we assembled the detectors in an octagon shaped ring, giving us a field of view of around 80 mm, this size will be good enough for small animal imaging. The detector was designed in such a way that if needed, a bigger ring could be constructed, the rationale behind this is that if we build the detectors and the casing to fit this octagon, if a wider field of view is needed we can just use the same detectors arranged in a polyhedron of the same edge size but with more sides, like for example if we were to go for dodecagon our new field of view would be 115 mm.

With the help of a former colleague and students we designed and printed not only the detectors but also a base where we could fit our detectors in the desired octagon configuration.

Fig. 4.11. Four detectors in octagon configuration

To help with the alignment we created holes on both the detectors and the base to help us fix the detectors to the base. This same holes were also very useful on some of the test, since they allowed us to fix the octagon to an optics breadboard that we used for the tests.

Fig. 4.12. Detectors on the optics table and 2D robot used for the tests

Due to budgetary reasons we could only afford to build four of the detectors, the main problem was with the scintillator arrays, we had bought them from a Chinese manufacturer and there were many bureaucratic issues when trying to finalise the purchase and having it delivered to our university. We bought only four arrays since we considered it to be enough for an initial test with the idea of purchasing more in the future, but we could not acquire four more arrays due to the aforementioned issues.

4.6. Tests and results

We had only four detectors but to compensate for this lack of detectors we used an optic breadboard to properly position our octagon base do one data acquisition, then we can rotate the whole octagon 45 degrees and acquire the data for the missing detectors. It is not an optimal solution but it is a working solution and is what we did in all of the following tests to emulate an octagon with 8 detectors.

Our group has a close collaboration with the group at UCM lead by Jose Manuel Udias, they have plenty of experience in PET image reconstruction, so after dealing with some issues with the reconstruction they were offered to help us. As such all of the 3D images presented in this work were reconstructed with a reconstruction software provided by UCM. Our group did the LUT generation and geometrical system specification.

4.6.1. Point source in the center of the field of view

For the first test of this system we performed a full detector characterization placing a ^{22}Na point source in the center of the field of view so that all detectors were properly illuminated by it.

Flood field images These images are useful to check that all pixels are clearly visible and distinguishable on our detectors. We see that the images are very homogeneous, a promising result. We still need to check the energy resolution and the spatial resolution to know how good our detectors really are.

Fig. 4.13. Flood field images for all 4 detectors

Energy Resolution To study the energy resolution we start from the flood field images, then select a well illuminated area on them, and from there select the pixels inside that area.

Fig. 4.14. Pixels selected to study the energy resolution on all detectors

Once the pixels have been separated from the background by thresholding the original flood images. We can use the events belonging to each of these pixels to generate energy spectra for the pixels. On these spectra we will find the photopeak corresponding to the 511 keV photons, fit a Gaussian curve to it and check its full width half maximum (FWHM), this measures the energy resolution of our detector.

Fig. 4.15. Energy resolution on different pixels on the 4 detectors

The mean energy resolution we obtain for all of the pixels shown above is 13.37, a very good value for a LYSO pixelated array.

Spatial resolution There are different ways to measure spatial resolution on a PET detector, but all of them share the same first step, draw a profile across the detector and measure how easy it is to distinguish the pixels from the background and from one another. The way to measure this difference is how the methods mostly differ, the more commonly used method is to measure the peak to valley ratio, the disadvantage of this method is that it does not take into account either the pixel shape (how well defined the pixel is in the image) or the distance between adjacent pixels. For this reason we prefer to use the resolvability index as defined in [57].

$$ResolvabilityIndex = FWHMofcrystalinfloodhistogram(Distance separating twocrystals)$$

Fig. 4.16. Spatial resolution of detector 1

Fig. 4.17. Spatial resolution of detector 2

Fig. 4.18. Spatial resolution of detector 3

Fig. 4.19. Spatial resolution of detector 4

This results tells us that it will be easy to resolve the pixels on our flood field image, thus look up table (LUT) generation will not be difficult for the reconstruction. The mean resolvability index across the four detectors is 0.35.

3D Point Source reconstruction The last step in this initial test is to check whether or not we are able to reconstruct this point source and locating it.

Fig. 4.20. Reconstructed point source on different views

Fig. 4.21. Profiles on the different views

With a full width half maximum of 1.27 mm on the axial plane, of 1.34 mm in the re-

maining planes and considering that our point source has a diameter of 1.8 mm, according to the manufacturer[72]. Taking into account that there are not geometrical corrections being applied to the system, we can expect the final resolution of the system to be somewhere around 1 mm.

4.6.2. Derenzo-like acquisition

For this experiment we used two motion stages from OWIS to create a small 2D robot that will allow us to place the point source on different locations of the field of view. The acquisition works in the following way, we set the robot at a certain position in space, we start an acquisition, then we place the source on the next location and acquire again, we repeat this process for all of the points we want to acquire in the space. Once this is finished we had to start the process again to compensate for the missing detectors, this is not the best option for this kind of acquisition, since the position repeatability of both linear stages will have an impact on the measurements.

All of this tests were carried out with a point source of ^{22}Na . We tried with our robot to emulate a small animal Derenzo phantoms with sections of 0.75mm, 1mm, 1.35mm, 1.7mm, 2mm and 2.4mm. The results are presented of figure 4.22.

Fig. 4.22. Derenzo-like acquisition

Due to the mechanical tolerances and our source being 1.8 mm in diameter, on this image the only section which is clearly visible is the 2.4 mm section. We reconstructed this section by itself and by looking at the profile we can assure that the distance between the centers of the pixels on the reconstructed images is 2.48 mm.

Fig. 4.23. Points separated 2.4 mm

These results are promising but we would need to perform a full system characterization and calibration to further improve our spatial resolution. In the current reconstruction no geometrical corrections are being applied due to the lack of a proper system calibration. This result confirms our previous expectations for our final resolution to be around 1 mm after the corrections.

4.6.3. SSLE LYSO array

Since we had already tested and characterized this detectors we knew they were reliable and for that reason we decided to check if Sub Surface Laser Engraved (SSLE) arrays could be used with SiPMs. We had already presented some initials results at [73] and we had been able to acquire images were we could clearly distinguish the engraved array using PMTs, but had not been able to replicate the experiment with SiPMs.

On the images we acquired with SiPMs the engraved array was very small, as if all the light was being drawn to the center of the array. We theorized that this might be due to the fact that the inter pixel surfaces were not acting as perfect mirrors and a good percentage of the light being emitted was lost, and only direct incident photons were detected by the SiPM. One big difference between SiPM and PMTs is the entrance windows that is used, PMTs used an entrance window thicker that the one employed by SiPM so we considered it a good idea to test the SSLE arrays using different light guides.

The SSLE array used is comprised of hexagonal pixels with a 0.7 mm side and an area of approximately 1.4 mm^2 . The array was engraved on LYSO block of $12.8 \times 12.8 \times 6 \text{ mm}^3$.

Fig. 4.24. LYSO SSLE array of hexagonal pixels with different light guides

Fig. 4.25. Energy spectrum comparison with different light guides on a SSLE LYSO array

On the above images we can see how the image quality improves as we use a thicker light guide. Proving that in fact SiPMs based detectors can be used with SSLE arrays, as

long as we attach a light guide to the engraved array.

The spectra presented here are not the ones obtained by selecting only the corresponding pixel regions, but rather those belonging to the whole crystal, in this sense we can see a curious behaviour of SSLE arrays, they produce a spectrum that resembles that of a monolithic array, rather than that of a pixelated array. A known drawback of using light guides is that they tend to deteriorate the energy resolution of the detector since spreading the light over a larger area means losing some of it as well.

Results from this work were presented at [74] and on [75]. Once we were sure of the feasibility of employing the new SSLE technology with modern radiation detectors we filed a patent [76] describing the invention.

For completeness sake we present as well the result obtained with a SSLE engraved array of 1 mm^2 squared pixels. This test was performed to asses that in fact using a 4 mm light guide we could easily detect the pixels on the flood field images obtained from SSLE arrays using SiPMs based detectors.

Fig. 4.26. Squared LYSO SSLE array using a 4mm light guide

5. ICOPET: A 4π COVERAGE PET IMAGING SYSTEM

In this chapter we will present a system that is currently under development in our group. Part of the work presented here is only theoretical at this stage. We present the design choices that led us to this particular configuration and the initial results from the detectors of the system we plan on building.

This system is intended to improve on many of the limitations of current PET systems, like the limited detection angle. This can be improved by adding rings to the system [77] but the optimal detection system would be one in which the coverage is the same for every point in the field of view (FoV).

A system with a higher coverage will not only improve resolution, but also the acquisition time and the dose required for the study will be minimized. Being able to acquire an image of the same quality while reducing both dose and acquisition time has always been one of the main goals in PET systems. Reduction in the acquisition time will allow a hospital to scan more patients per day, and will also reduce the time a patient has to be on the scanner, which is not a very comfortable situation. It is obvious that a reduction in dose will always be welcomed, it will not only be better for the patient but also for the hospital personnel handling and administering the tracer to the patient.

5.1. Why a full coverage PET system

The idea of increasing the coverage on a PET system is not new and systems with a spherical design aimed at achieving a better coverage were presented in the 80s [78]. Different groups around the globe agree that one of the biggest chances for improvement in PET resides in new system configurations that maximize the sensitivity of the system and the easiest way to achieve this is by redefining scanner geometries to increase the detection rate. [77],[79].

In particular the group led by Simon R. Cherry has put a great emphasis over the last years in the need for a total body PET system[80],[81]. Their efforts has led to the creation of the EXPLORER scanner, a total body PET that has proven capable of improving acquisition time and sensitivity on human studies[82].

These publications state that by improving the coverage, a 40 fold increase in sensitivity can be achieved for whole body imaging and 4-5 times increase for specific organs like the brain or the heart. A regular PET scanner geometric sensitivity is under 5% inside its FOV. When studying organs positioned well inside the FoV only 3-5 % of the photon pairs are acquired, because radiation is emitted isotropically and only this small percentage is detected by the detector rings.

In nuclear medicine images, the image quality is directly related to the number of

decay events that can be detected. On [83] the authors estimate the signal to noise ratio (SNR) of the image is proportional to the square root of the number of detected events.

$$SNR \propto \sqrt{n} \leftarrow n \approx kAG\epsilon^2T$$

The number of detected events will depend on the activity present in the scanner's field of view (A), the geometric coverage of the scanner (G), the detector efficiency ϵ , the acquisition time (T) and some other patient specific factors included in the constant (k). We can easily influence on two of this factors, the acquisition time and the activity injected to the patient, but they will have a negative impact for the patient, ideally we would like to minimize these two parameters without affecting the image SNR. This leaves us room for improvement only on the detector efficiency and the scanner's coverage, on this chapter we will present designs aiming at this particular objectives.

Ring based scanner topologies, also present a problem due to the way that line of responses sample the field of view, giving a non uniform sampling over the whole field of view, as can be seen of figure 5.1.

Fig. 5.1. Sampling error on ring based scanners, reproduced from [84]

This error can be corrected by improving the way LORs are distributed along the FOV.

A secondary effect of improving the geometrical coverage is the reduction on the amount of random events. Random events are annihilation events on which LORs are wrongly assigned due to the fact that photons belonging to different annihilations are detected together and assumed to belong to the same annihilation event. By improving the geometric sensitivity of our system we maximize the number of detected photons thus minimizing the probability of wrongly assigning LORs.

An increase in sensitivity means as well an increase in detection rate. Increased detection rate directly translates into a need for faster electronics capable of withstanding very high count rates over the whole scanner.

The greater advantage of improving the SNR on a PET image is that it enables us to reduce the dose administered to the patient as well as the acquisition time. The results published in [82] prove that by improving the geometric efficiency, a whole body PET image of diagnostic quality can be acquired in as little as 37.5 seconds, opening the door for better dynamic studies and the use of isotopes with shorter half lives. On the same study one of subjects was injected only with a 10 % of the dose administered to others and it was still possible to acquire a good quality image.

Fig. 5.2. First human studies results from the Explorer scanner, reproduced from [82]

5.2. Geometrical considerations and configuration

In an attempt to improve the geometric sensitivity of a PET scanner, we can assume that the optimal geometry for a PET scanner is a sphere with the subject located at its center. However, current γ ray detector technologies based on scintillator crystals and photodetectors do not facilitate the design of a smooth spherical geometry due to their rigid flat morphology. Platonic and Archimedean solids can be used to approximate to a sphere, resulting in a detector geometry with flat faces, that can be built with the current technology.

Fig. 5.3. Platonic Solids, from [85]

Fig. 5.4. Archimedean Solids, from [86]

The idea of using this kind of geometry on a radiation detector has already been considered by other groups. On [87] the authors propose a brain PET design based on a dodecahedron. On [88] the authors propose a coded spherical configuration, with 4 isotropic field of view that can be used for coded aperture and Compton imaging.

When choosing a geometrical configuration we established certain requisites that the geometry should meet:

- Equal faces better than mixed elements. Having different faces will not only add difficulty to the electronics and physical design of the system, but will also have a negative impact on the sampling error, different face geometries will produce different LORs densities along the FOV. Symmetrical and equidistant arrangement

of detectors promotes homogeneous sensitivity. This means that for our design Platonic solids are preferred over Archimedean solids

- Better to have the maximum number of diametrical opposite faces since this will ease LOR positioning and image reconstruction
- The chosen solid should not contain sharp angles between adjacent faces to minimize the scanners blind spots. This translates into choosing the solid with the highest possible dihedral angle.

The solid that meets all of this requirements is the convex regular icosahedron, this Platonic solid has 30 edges and 20 equilateral triangle faces, five of its faces will meet at each of its twelve vertices. A regular icosahedron has 6 symmetry axes of order 5, the lines that join opposed vertices; 15 symmetry axes of order 2, lines joining the center of opposing sides; 15 symmetry planes, containing each couple of opposed coplanary sides; and a symmetry center. This all add up to a total symmetry order of 120: $2 \times (6 \times 5 + 15 \times 2)$ [89]. Icosahedrons occur in nature, like in the capsid of viruses and the head of bacteriophages, they are also an element of pop culture thanks to the role playing game Dungeons Dragons that popularized the use of 20 face dice for role playing games.

(a) Twenty face dice

(b) Bacteriophages

Fig. 5.5. Twenty face dice and bacteriophages, from [90]

Once a geometry for the scanner was chosen, the next step was to evaluate what else could be improved in order to further enhance the SNR of our scanner. The other parameter up for improvement was the detector efficiency. Common SiPM detectors are based on a squared geometry for two reasons, they can be easily tessellated and are also easy to manufacture with the current technology.

There are only three possible tessellations of regular tilings, these are known as euclidean tilings. Regular tiling can be formed with triangles, squares and hexagons. It

is also possible to combine these and other polygons to generate what are known as Archimedean or semiregular tilings. The problem with these and other non regular tilings is that, as we have already discussed, having a non uniform detector geometry produces a non uniform space sampling.

Fig. 5.6. Regular tilings, from [91]

We are not the first ones to consider using an hexagonal tessellation for a gamma detector, in fact in his seminal paper [92] Anger HO, proposed to place the phototubes in an hexagonal array, in this case the decision might have been influenced by the fact that the photomultiplier tubes used to be round. As the technology improved PMTs started to be squared, making it easier to tessellate in square arrays. But with the introduction of silicon photomultipliers using silicon wafer microfabrication techniques many new geometries are possible.

Considering that the optimal solution for reading out an array of detectors will be the one the that better distributes the input signal, in this case, the light emitted from the scintillation crystals. A more homogeneous collection of light can be achieved if the centers of all detection elements are at the same distance to one another. This is not the case in a rectangular array since the distance to the diagonal neighbour larger than the distance to the lateral or vertical neighbours. In an hexagonal array however the distance to each of its six neighbours is the same, making the hexagonal array a better candidate for radiation detector tessellation.

Fig. 5.7. Hexagonal Pixels vs Squared Pixels, from [93]

Finally if we are going for hexagonal pixels, why not also go for hexagonal scintillator pixels. The main drawback for this was in the fabrication process, the creation of a scintillator array is already quite expensive for squared arrays, it will be even more for hexagonal ones. Another problem with hexagonal pixels is the packing fraction, if we move from 4 sides to 6 the amount of reflector present in our array increases, worsening our packing fraction, making our detector less sensitive. However, with the new developments on SSLE technology we can overcome this packing fraction issue as has already been proven in our group [94], making possible to use hexagonal scintillator pixels.

There is one more consideration to be taken into account, the amount of light lost in every reflection. The smaller the angle in the corner of the scintillator, the greater the chance that some of the light might become trapped in the scintillator and thus not detected. Ideally, all of the light should be collected on the detector side of the scintillator crystal, for this reason geometries with the smaller vertex angle are preferred.

5.2.1. brain PET and small animal prototype

Recently there has been a growing interest in dedicated brain PET scanners[95],[96], because PET is still the imaging technique better suited to study brain alterations in functional images. Functional MRI (fMRI) is a good contestant in the field of functional neuroimaging but due to the nature of this imaging modality it can not be used to study neuroreceptors and metabolic brain responses in the same way PET can. Dopaminergic radiotracers like F-DOPA are used on the examination of patients affected with Parkinson's disease[97], dopamine dysfunction can be used to select a better treatment for schizophrenia patients[98], new radiotracers focusing on other neurotransmitters are also available for research. One drawback if we compare PET images to MRI images is the resolution, PET resolution is normally not as high as MRI, but as was discussed on section 5.1 resolution on organ dedicated scanners can be improved using full coverage scanners.

Animal models play a fundamental role in biomedical research, they are used in the development of new pharmaceuticals, in disease progression studies, brain function studies and a very long list. Small animal imaging as a non invasive imaging modality allows

us to perform longitudinal studies, needed to study how a disease or a condition evolves with time. Small animal PET systems with very high resolution are needed for these studies [99], and as we saw on section 5.1 scanners with better geometric coverage provide improved resolution.

For the above mentioned reasons we propose two different designs, one for a dedicated brain PET scanner and one for preclinical imaging, figure 5.8, both sharing certain geometric traits that helps us achieve a better geometric coverage. We are calling this designs **icoPET** due to their icosahedron based geometry. The small animal scanner is designed as a scaled down version of the brain PET scanner. The proof of concept icosahedron for preclinical imaging is being built with the following physical dimensions: 20 faces of 155 mm of edge; 775 mm of perimeter for the pentagon defined in the upper cap, 234 mm diameter for the inscribed sphere.

Fig. 5.8. Proposed PET designs

A detailed diagram of a face is shown in figure 5.9. Each face is coupled to ten hexagonal monolithic LYSO laser-engraved scintillator crystals (SSLE) [94] (gray in figure 5.9). The size and pattern of the engraving fit the size of the pixels of the Silicon Photomultipliers (SiPM) set on top of the scintillator (yellow in figure 5.9). There is a total of 61 pixels per crystal. The number and size of scintillator crystals can be argued as a favorable ratio between packing fraction and production costs. On the other hand, the thickness was selected to be 10 mm as an optimum trade-off between stopping power and minimization of the parallax error, thus aiming to reduce the degradation of spatial resolution at off-center positions, although we have also designed an SSLE engraving that provides Depth of Interaction (DoI) [100]. This arrangement results in a geometrical efficiency of 73% with respect to a 4π coverage.

Fig. 5.9. icoPET face design

In figure 5.10 the Michelogram of the icosaedron is presented. A “Michelogram” is a common and intuitive tool to visualize data combination. The faces of the icosahedron are displayed in both axes and allowed coincidences are marked. In the present design, three different types of coincidences are considered: direct (D, red), when the normal of both facets are parallel; cross sharing an edge (A, yellow), when one facet shares an edge with the direct facet; and crossed in a vertex (V, green) when one facet shares just a vertex with a direct face. There is a sum of 10 pairs of faces in direct coincidence, 35 adjacent coincidence and 60 in vertex-sharing coincidences. The maximum angle subtended by faces in direct coincidence with respect to their normal is about 35° . In the case of cross edge sharing faces, the maximum angle is 45° while for vertex sharing facts the widest angle reaches 64° . This angle depicts the field of view (FoV). Thus, the scanner sweeps a FoV of 152 mm of diameter.

Fig. 5.10. Michelogram

We decided that when building the actual system, the vertices could be truncated a

little to add sensors or to include other imaging modalities in this design, like including micro CT x-ray sources thus transforming our system in a PET/CT scanner. The option for other sensors could include as well wireless receivers for sensors connected directly to the patient without needing to add cables, like for example an EEG sensor with a IR output [101].

This design study along with the some previous simulation results have been presented by our group at some international conferences[102],[103],[104],[105]. Below are some of this simulation results, figure 5.11.

(a) Histogram of a punctual source at the center emitting in every direction

(b) Sinogram of a point source placed at 3cm in the Z-axis. Histogram at angle azimuth of 45°.

Fig. 5.11. Results presented at [102]

5.3. hexagonal SiPM detector

We did not know that manufacturing hexagonal detectors was feasible in the manufacturing sense. First we checked if it had been done and if we could find a company willing to manufacture this new kind of sensor for us.

After some searching we found that in fact hexagonal photomultipliers had already been used before [106]. They were used for a Cherenkov telescope [107],[108] on the CTA collaboration. From this we got two very important pieces of information:

1. Confirmation that it was possible to manufacture hexagon shaped SiPM
2. Hamamatsu already had experience with this kind of detector and they might be up for it.

(a) Hexagonal detector, from [106]

(b) PCB used on the Cherenkov telescope, from [109]

Fig. 5.12. Detectors used on the CTA collaboration

There were however some things that were not good about these hexagonal detectors for our particular application. The detectors used for the telescope had 4 different channels in the same hexagon, we preferred to have only one channel per hexagon. The fill factor was not as good as we would like. The detector was also quite big for our application. Still the fact that there was already a similar device was a very good head start.

We discussed with the engineers in Hamamatsu about what we wanted and finally came up with a solution that fitted our needs, this process took some time since it was a custom made detector. First we considered using squared pixels to fill out an hexagon but the fill factor we got was very poor, on the final design we opted for an hexagonal pixel with 2.25 mm of side.

(a) Hexagonal detector first designs

(b) Hexagonal final design proposed by Hamamatsu

Fig. 5.13. Hexagonal detector designs

Hamamatsu also agreed to provide us with the detectors arranged in an hexagonal array of 61 pixels, with five pixels on each side, giving a length of 17.61 mm. Hamamatsu provided as well the front end electronics, an ASIC based design, similar to the one on the C12680-3050NA-08 module provided by Hamamatsu, so that we could get to work as soon as we received the detectors.

Fig. 5.14. Hexagonal detector array developed for us by Hamamatsu

Parameter	Value
Effective photosensitive area per channel	10.39 mm ²
Number of channels	61
Pixel pitch per channel	50 μ m
Number of pixels per channel	3980
Spectral response	320 to 900
Peak Sensitivity wavelength	450 nm
Photon detection sensitivity	40%
Break down voltage	53 $\pm$ 3 V
Dark current per channel	Typ. 150, Max. 570 nA
Crosstalk probability	3%
Afterpulse probability	3%
RC constant	45 ns
MPPC gain	1.7 $\times$ 10 ⁶

Table 5.1. Electrical and optical characteristics, hexagonal MPPC array

5.3.1. Encoding schemes for hexagonal detectors

We had the hexagonal detectors assembled in an hexagonal array, and now we needed to develop a readout scheme that could actually work well in positioning scintillator crystals on an hexagonal distribution.

Regular position encoding schemes [110],[111],[112] start with the assumption that you have a squared detector with a regular pixel distribution thus you can encode information in two Cartesian coordinates to later on acquire the position information. As we discussed before, on section 5.2, on old gamma cameras a bee hive distribution of detectors was used and they were read out using the standard Anger encoding schemes, but

it in our experience this approach will not provide very good results, since the we will end up connecting a different amount of channels to each line of the encoding schemes. This directly affects the homogeneity of the detector and thus the final image SNR of our scanner.

Silicon photomultipliers can be thought of as charge generation devices, whenever a photon is detected the detector generates a charge pulse that is then translated to a current pulse thanks to the front end electronics. As we saw on the first chapters 2.3 if we increase the size of the detector element we increase its capacitance, this increase in capacitance have a negative impact in the timing of the detector and generally will need to be compensated on the electronics. When we use an encoding scheme normally we would connect several of these detectors to a single analog readout line that will then be used for position encoding. Meaning we are actually interconnecting several photomultipliers, this increases the charge seen by the electronics and affects the position, energy and timing resolution we are able to achieve. For this reason some authors have proposed other "non conventional" encoding schemes [113],[114],[115]. These methods however might not be optimal for our design, since we plan on using very small crystals and these methods have all used $3 \times 3 \text{ mm}^2$ crystals, leading to one to one coupling schemes, it is important to point out that on [113] the authors also include DOI information. We considered different multiplexing schemes and simulated how some of them might look like. For this we used GATE and performed a simple optical simulation to check how will light be distributed on our pixels, we only simulated a small section of the detector, since with this simulation we can estimate more or less the behaviour of the whole detector. We are assuming that on a pixelated array light does not spread further than to the neighbouring pixels.

Fig. 5.15. Simulation study of hexagonal crystals

In the end we decided for the two encoding schemes shown below. The one on the left is the easiest one to implement, in this scheme instead of taking X,Y coordinates we use diagonal coordinates thus maximizing as much as possible the homogeneity in the

detector. The one on the right is a bit more complex, in this design each channel represents an analog input channel that will later on be used to create a weighted sum from which position can be determined, first we determine to which 7 element hexagon the event corresponds and then using the information from the neighbouring pixels we can detect the actual event position. There are some drawbacks with this method however, one is the loss in resolution on the border pixels, but this will affect any kind of encoding scheme, since for this events there will always be less sensitive surface than for the rest of events. Another and maybe its main drawback however is that it requires 6 input channels, two more than the more conventional approach. More on this on section 5.4.4.

Fig. 5.16. Encoding schemes proposed for hexagonal detector arrays

5.4. Proposed Readout System Design

There are some very important constraints to take into account when working with a system like this. The most important one for our design are the maximum supported count rate and the amount of analog input channels.

Encoding is so important in a design like this because it allows us to reduce the number of analog inputs our system needs. Each analog input means another ADC that we add to our system, this means more digital information needs to be transferred and processed later on. Having a data rate of several GB/s can create bottlenecks in our system, specially due to the speed of storage elements. Which is why is better to get rid of unnecessary data as soon as possible, as long as we are able to achieve a good system performance.

A lot of attention has to be paid to the readout design in order to avoid the aforementioned bottle necks that can limit the maximum count rate of our system. Our design greatly improves the solid angle coverage of commercial PET scanner designs, the improvement in geometric coverage entails a boost in sensitivity, which is the same as saying that we expect a very high count rate. If we limit the maximum count rate of our system due to an error on the readout design then we are basically wasting the benefits of our geometry.

We propose two very different approaches, one is a real time data acquisition system based on a Virtex-6 FPGA, quite similar to what we used on the system described on the previous chapter. This is a system with a lot of flexibility and that we know works well with SiPM based detectors. The other design uses an ASIC as the front-end and ADC of the system, thus minimizing the amount of analog elements on the system, however there is one big drawback with this design and that is the maximum possible count rate of the ASICs that are currently available.

The scanner has 20 faces, each of the them comprised of 10 arrays of 61 hexagonal SiPMs. Giving us a total of 12.200 SiPM channels. Digitizing and storing the information from all of this channels whenever an event is detected makes absolutely no sense, since in the end we only care about the event position, energy and timing and whether or not it was a coincidence event. In PET we will only use coincidence events for image generation, but single events information is useful for detector characterization and troubleshooting. Even if our system will normally uses coincidence information it is good practice to be able to acquire single data if needed.

Our group already presented some simulations that allow us to estimate the maximum number of coincidence events per face to be around 400 thousand counts per second [103]. In this simulation a dead time of 200 ns was estimated for each scanner face, with 100 ns pile-up, using a coincidence time window of 2 ns and an energy window of 350-650 keV.

5.4.1. Real time ADC based system

On this system it is mandatory to include some sort of analog multiplexing, to reduce the number of analog inputs. The first step is to ensure that we use an encoding scheme that leaves us with the minimum possible amount of signals, in this case 3, one for each of the position coordinates and one more for the energy. It will be good to include as well a digital timing signal, this digital signal could be the output from a fast comparator and will serve two purposes, one is to provide timing information and the other to detect coincidence events by propagating it through out the system.

We can obtain as with the SiPM detector on the previous chapter 4 analog output signals X_A , X_B , Y_A and Y_B then we combine these to obtain three new analog output signals

$$X = X_A - X_B$$

$$Y = Y_A - Y_B$$

$$En = (X_A + X_B + Y_A + Y_B)/4$$

This first stage is already allowing us to go from 61 input channels per array to only 3. But we still have 30 analog outputs for each of the faces of the system, leaving us with 600 analog outputs which is a lot better than before, but still it is very difficult to manage that many input signals, in a system that is supposed to be small and compact.

If we can use an extra signal to encode from which detector in the face of the scanner came the event, we could combine the signals from all detectors on the same face, reducing the 600 signals to only 60. We would then need a combiner stage, this stage will combine the signals from all of the arrays belonging to the same face giving us:

$$X = X_1 + X_2 + ...X_{10}$$

$$Y = Y_1 + Y_2 +Y_{10}$$

$$En = En_1 + En_2 + ...En_{10}$$

For this analog summation we can use an RF combiner like JEPS-12-10 from mini-circuits, with a enough bandwidth to not degrade our signals.

This would work if we assume that there will not be two events occurring at exactly the same time over the same face of the detector. However, as the number of counts increases the chances of such an event (pile-up) occurring, increase as well, so we need to add a way of ensuring that this does not happen. There is still the problem of encoding the array position information (from which array the event came from) both problems can be solved on the digital domain.

By using comparators on the incoming energy signals we can obtain digital pulses ($DEn_1...Den_{10}$) indicating when the energy on a certain array is above a threshold level. We can encode this signals as if they were analog information by using a weighted sum on them: $AEnOut = (Den_1 * W_1 + ...Den_{10} * W_{10})$ this will not only provide the incoming detector information but also will serve as a pile up rejection element. If two events were to be detected at similar times the voltage level on AEnOut should fall in a non valid range, thus indicating that a pile-up event occurred. It is important to point out that there should also be a digital output version of AEnOut that would be used for timing and coincidence detection.

With all of the above for each of our faces we would have 5 output signals, 4 analog and 1 digital:

- X : x event coordinate
- Y : y event coordinate
- En : event energy information
- AEnOut : analog encoded array position information
- DEnOut : digital version of the previous signal, used for timing and coincidence detection.

Now the system will require 80 analog input signals and 20 digital signals, which is lot more manageable than the previous 600 and should not be so difficult to achieve with the current technology. If we were to select a system like the PicoDigitizer 125 used on

the previous chapter, we would need 3 units of the 32 input channels versions to achieve this.

The digital signals would be connected to each of this PicoDigitizer units, so that each of them could tell if an event had been detected on another face of the system, solving like this the coincidence detection on the detector level. Coincidences detected like this could only be considered rough coincidences, to further enhance timing an internal TDC would give us a better timestamp that would later on be compared with the timing information from the other detected event.

The main drawback of this system is that it has a certain complexity in the amount of analog processing done to the signals prior to its conversion. This could worsen the SNR of the signal and of the acquired images.

To achieve this design we think it would be manageable with three stacked PCBs.

- Charge distribution network: this PCB would be entirely passive, employing only resistors and connectors. It will be directly connected to the hexagonal SiPM.
- Active Stage: The second PCB will contain the amplifiers used to obtain the X,Y and En signals for each of the detector arrays, so entirely analog.
- Combiner Stage: This board will be the most complex one since it will carry the analog combiner and the comparators. It will be a mixed A/D board requiring a careful ground and power plane design to minimize interference on the digital signals and avoid oscillations on the comparators.

It is important to point out that the level of encoding used on this design is more a system design requirement than a design choice. If we were to use too many analog input channels just the bulk of the cabling needed to achieve such a system will render this scanner impractical and very difficult to build and use from a mechanical perspective. Cabling increases as well the chances of failure due to a broken connector, a very common error on any scanner or medical equipment.

Power consumption is another worry with this design, the use of so many analog comparators increases considerably the power requirements of the system. But still if we were to use ADCs instead of comparators the power needed will be even more, so as was mentioned before, heavy encoding in this particular scanner is far from optional.

5.4.2. ASIC based design

Application specific integrated circuits(ASICs) have been present for some time on nuclear medicine detector designs[116],[117],[118] and that is because they are a tremendously good fit for these detectors. ASICs can include signal conditioning along with some level of digitization and digital processing in a chip smaller than the detector array to be used with a very good SNR and incredibly low power consumption.

There are however some limitations when using ASICs, specially if they include digital elements. A common approach for ASICs used on PET detectors is to use time over threshold (ToT) to measure the energy of the events [118], this works very well when using one to one coupling, where instead of detecting the position of a small crystal inside one of the detectors of the array we are basically detecting which array element is the one that acquired the most light and we can then assign the event location to said element. If like in our case the crystal elements are smaller than the detector input channels ToT methods have a very hard time acquiring position information because the relationship between ToT and detected light is non linear, there are some groups proposing methods for improving linearization[119], but so far ASICs using this method are generally discarded for small animal designs because of this reason.

There are also analog only ASICs, that can be used to implement most of the charge distribution and signal conditioning needed[120], but since ASICs are generally designed with a specific problem in mind if we wanted to use an analog only ASIC we will have to basically design it for our system, this is not only out of the scope of the current thesis, but will also be very expensive.

There is however one ASIC manufacturer with plenty of experience in high energy physics (HEP) based designs, this manufacturer has also been implied in European efforts to design ASIC based scanners[95], so they have built ASICs that work very well for PET scanners. One of such model is the TRIROC ASIC which includes charge integration and pulse height detection as measurement methods. Both charge integration and pulse height are known to have a linear relation with the amount of light detected, making them a better choice than ToT for PET scanners.

This TRIROC ASIC comes with 64 analog input channels specially designed for SiPM detectors, so in our case we will require only one ASIC for each of the detector arrays. The ASIC includes as well some SiPM specific characteristics like fine tuning of the operating voltage applied to each of the channels in the detector array, this can be used to improve the gain homogeneity of the detector. Configurable triggers for each of the SiPM channels, that help in reducing the amount of scatter events detected by allowing a fine tuning of the detection threshold. Good timing measurements over all of the 64 channels. There are also output trigger signals that can be used to know when has an event been detected by the ASIC. Overall this ASIC seems like a perfect fit for our design, but it has a drawback and that is the maximum supported count rate, which is 50 Kevents for each ASIC.

If we consider that events will be distributed more or less evenly across the surface of each face, the maximum allowed count rate with the ASIC will be 500 Kevents, enough for our system. However, if two events were to arrive at the same detector on a face, then the maximum count rate will be that of the ASIC, which is 8 times less than what we expected. The chances of two events arriving at exactly the same detector in a small time interval are not so high as to make the use of this ASIC impossible. We can design a

prototype for our system using the this ASIC, the benefits of using an ASIC far exceed the small loss in count rate that it will imply. One more advantage of an ASIC based design is that if a new and faster ASICs were to come out, with better maximum count rates, it will be quite simple to replace just this particular element of our processing chain. This is not a crazy idea considering the evolution of the ASICs designed by this manufacturer (Weeroc).

Fig. 5.17. Triroc ASIC, from the Weeroc website[121]

Leaving aside this maximum count rate limitation, we can consider a scanner design built around this ASIC. The ASIC is provided in 12x12mm BGA package, so it fits perfectly with our 17.61 mm hexagon, leaving room for necessary auxiliary components and board connectors. In this design we can picture each of the detector arrays on a face connected to its own ASIC and all of this ASICs being read by a single master FPGA. We will end up with a total of 20 FPGAs, one on each of the faces, connected to 200 ASICs. This FPGAs could either connect directly to a PC or a custom main controller board could be used. The main advantage of using a custom build main controller board is that said controller board could be used for coincidence sorting, thus reducing the amount of processing to be done by the PC handling the image processing and reconstruction.

On this design coincidence detection could be left to the face FPGAs by interconnecting them using a 20 wire digital bus. This bus will carry the trigger signals for each of the faces, so whenever an event was detected all other FPGAs would be informed of it. This information serves to mark the event as a possible coincidence with detector X and assign it a timestamp so that later on, coincidences will be easily arranged by the coincidence

sorter.

Compared to the previous design there are some clear advantages. The most obvious one is the reduction in SNR and size of the system. With this design there will only be two PCBs for each face and all signals will be digitized as soon as possible minimizing the degradation of signal quality due to the analog processing. Power consumption wise ASICs are way better than fast ADCs (> 50 MHz), this particular ASIC for example requires only 10 mW/channel, so the consumption for all the ASICs in one of the faces will be around 6 W.

The most complex part in this design will be the PCB connecting to the 10 ASICs on each face. This board requires the use of high speed PCB connectors able to withstand the expected throughput of data. These FPGAs should also be able to detect rough coincidences at least.

In this design there is absolutely no encoding present, but rather a one to one sampling scheme which is only possible thanks to the small size and power requirements of the ASIC.

5.4.3. First results: single channel acquisition

We wanted to know the shape of the pulses produced by this system and how reliable our simulations were when compared with the actual device. To test this we first used an hexagonal monolithic crystal that should distribute light over several channels for each detected event and later used a small squared matrix array with LYSO crystals of $1.3 \times 1.3 \text{ mm}^2$ in which we expected light to be more focused on the main incidence pixel and the neighbouring pixels.

Hamamatsu provided us with a module that included all the necessary elements to read out each channel on the detectors one by one. An important part of this module is the ASIC provided by Hamamatsu and used as a first signal conditioning stage on this board. This is an analog ASIC providing a gain of -1 and applying a gain homogeneity correction to compensate for the breakdown voltage differences on the pixels of hexagonal array.

Fig. 5.18. Experimental setup used

Making some adjustments to the FPGA code developed for the acquisition of the detectors in section 4 we acquired the output signals for individual pixels. Only 14 channels were acquired out of the 61 in the array, the pulses here presented are the mean pulses of 100.000 acquired events, events were previously selected so that only events focused on the center pixel were stored, events where the largest amplitude was on the center pixel. For the energy spectrum generation a separated channel was acquired, this channel is provided by the ASIC and is a sum of all the analog channels on the detector.

On All of the results presented from here onward a ^{22}Na point source was placed at approximately 5 cm from the surface of the scintillator to illuminate the detector as evenly as possible without losing too many counts.

Fig. 5.19. Monolithic LYSO Hexagonal crystal

On figure 5.19a we see how almost every pixel in this acquisition gets some of the light from the event. This means that light in this monolithic crystal is distributed across several pixels. We also get a very nice energy spectrum from this crystal.

To test that light was more focused on pixelated arrays, we used a 1.3x1.3mm squared matrix array of LYSO pixels and repeated the experiment.

Fig. 5.20. Pixelated LYSO array

The pixelated matrix array as expected focuses more light on only a few of the pixels, which are always the neighbouring pixels of that with the most activation.

One limitation of this study is that we acquired only 14 channels from the detector, leaving one for the energy of the system and another one was used as a check to ensure that no noise was being added to the measurements. We considered performing another acquisition making use of the 32 channels available in our data acquisition system but ended up discarding this idea, since for such a simple experiment just this small tests were enough, besides we had already ordered the TRIROC ASIC and with it we could acquire all 61 channels at once.

5.4.4. Analog Multiplexing Output, design and results

We decided to test first the simplest encoding scheme we could come up with and see if we were able to acquire an image with enough quality. To test this we planned on using four different scintillator configurations, first a monolithic LYSO crystal covering all of the detector, second a small squared LYSO matrix with a pixel pitch of 1.28 mm, a larger LYSO with a pixel pitch of 1.4 mm covering the whole detector and finally we decided to test as well the same SSLE hexagonal matrix used on section 4.6.3.

The circuit developed for this is quite similar to the one used on chapter 4 with the difference that we distribute the pixels in diagonal lines instead of rows and columns. The idea is that, like this we can cover all of the detector and obtain a similar reference, to what we used to obtain when using X/Y coordinates, just that the new coordinates will be rotated.

The input to our circuit is not as it was on chapter 4 taken directly from the detector, but rather we decided to use the output from the ASIC provided by Hamamatsu. This ASIC not only amplifies the signal but also reduces the coupling between pixels on the

same detector array. The idea is to first try this to ensure that our encoding scheme works and on another iteration add an analog charge distribution network without using the ASIC and see if our encoding still works.

Monolithic LYSO hexagon We got the same hexagon shaped crystal that we expected, this meant that our encoding algorithm in its simplest form works. Below we include as well the energy spectrum obtained.

Fig. 5.21. Hexagonal LYSO crystal on a hexagonal array

On figure 5.23a we can clearly see the hexagonal shape of the crystal and how all of its surface is properly illuminated, without any gaps or black holes on the image. As was expected the energy resolution for this monolithic crystal is quite good, 14.2.

LYSO array 1.4 mm pitch Considering that these are the first result and we are testing this system without any light guides or any other medium that could help dispersing the light and thus improving the positioning, we are quite impressed with these results. It is very important to point out the effect that using the ASIC in the first stage can have on this circuit. This ASIC not only amplifies our signals but also reduces the negative coupling effect that could happen with a completely passive charge distribution network.

Fig. 5.22. Flood field image of a pixelated array, with 1.4 mm pixel pitch

Taking a profile on one of the rows of pixels on this image we can now check the resolvability index. The mean resolvability index for the profile shown on figure 5.22 is 0.33, so we can safely state that with this encoding scheme it will be feasible to resolve the pixels in this flood field image.

(a) Spatial resolution study

(b) Energy resolution study

Fig. 5.23. Hexagonal LYSO crystal on an hexagonal array

As a sanity check we performed as well an energy resolution study, figure 5.23b. The mean energy resolution over the selected pixels was 14.5, a good result for a pixelated array. Another important fact about this result is that as happened with the monolithic crystal, in this case we can also appreciate the entirety of the pixels without holes or gaps in the image, making of this a very satisfactory result.

SSLE hexagon We tested as well the SSLE array we used on section 4.6.3 and acquired the following image.

Fig. 5.24. Hexagonal SSLE array of hexagonal pixels

On this test we did not use any light guides, to test if we were able or not to detect the pixels even in the worst possible conditions. On the image the pixels are clearly visible, they are a bit close to one another, but as we proved on section 4.6.3 this can be easily fixed by using a light guide. The area that has a lot of events on the top left corner is due to some physical damage that the array suffered some time ago.

We can then conclude the test as a successful one and safely state that this detector using this encoding scheme will be able to resolve the pixels engraved on a monolithic LYSO crystal using the SSLE technique.

5.4.5. ASIC

Weeroc currently provides a data acquisition board that can be used to test their ASIC. The board was designed for a specific experiment so it comes with two SAMTEC connectors that can be used to connect directly to the ASIC inputs. It also has several SMA connectors that are very useful for debugging, thanks to internal probes built into the ASIC that can be programmed from the user interface provided by Weeroc. Powering this test board is very simple, it can be powered just with a USB or it can also be powered using a bench top power supply. The same USB that can be used for power is also used to send data to the PC. One more good thing about this board is that since it was built for characterizing the ASIC it has many test points built into it, the bad thing is that they are not very well documented. There is a Cyclone II FPGA on the board that controls the

ASIC and handles communication with the PC.

This board is great since it gives you a good starting point. Although, it has some limitations like the fact that the current data acquisition software provided and the firmware used, at the moment, further reduce the maximum possible event rate of the ASIC. This should not be a concern for some first experimental tests, but in our case it limits the usability of the board since in order to acquire a large number of events the system will have to stay working maybe for days, and the data acquisition software is not very robust so it might be prone to failure.

We decided to test this board with two different scintillator configurations that will provide us with enough information as to assess the ASIC position and energy resolution. First we tried a monolithic LYSO hexagon, same size of the detector and second we planned on testing a squared array with 1.28 mm pixel pitch.

Since the connectors included in the board were not compatible with our detector we had to design an interface board to adapt the system to our needs.

Fig. 5.25. TRIROC evaluation board and adapter board for hexagonal SiPM arrays

Monolithic LYSO hexagon We started using the recommended configuration for the ASIC to be used with a SiPM detector of similar characteristics that ours. The results were not what we expected, the ASIC seemed to be saturated all the time.

We tried many different configurations, using different breakdown voltages, adjusting the fine tuning parameters on the inputs to fix the gain differences on the pixels. But were

unable to acquire a good energy spectrum with this crystal. Our impression is that this crystal gives too much light for this ASIC. That the ASIC is intended to be used with smaller crystals giving less light. There is also the option of reducing the breakdown voltage to make the detector less sensitive, but if we do that we risk working on a voltage level where the detector is barely sensitive thus acquiring only events with enough energy to trigger the few remaining sensitive pixels on each detector.

Fig. 5.26. Spectrum of the two data outputs offered by the TRIROC ASIC on a monolithic LYSO crystal

Even though we are not satisfied with the acquired energy spectrum what we can still use the acquired data to generate a flood field image. An interesting detail on this spectrum is the "High gain" Graph on figure 5.26, in it we can see energy quantas that look quite similar to the plot we get when detecting single photons on a SiPM, just that in this case this is related to single channel activation, thin can be checked by looking at the energy levels on the spectrum.

Fig. 5.27. Flood field image generated from combining the two outputs, monolithic LYSO crystal

To obtain this image we combined a weighted sum of the two different measurements provided by the ASIC, one is the Low Gain signal and the other is the High Gain signal. Because of how triggers work on this ASIC, a channel is only acquired if it goes above a certain threshold level, when using this crystal we see that for many of the triggered channels there is not actual signal on the Low Gain side. Our thoughts behind this, is that although light is reaching the detector channel, it is not enough light for the ASIC on the low gain side. In the high gain side we can see that many of the channels are saturated but while some other have very small readings. Overall we think that this ASIC couples poorly to monolithic crystals, we have been discussing about this with the manufacturers to see if we can come up with a solution to use this ASIC properly with this kind of crystal.

What we can actually do with the information provided by the ASIC is study the number of channels that fire with every photon detected and what channels fire together, this will give us an idea of how much is light spread across this detector.

Fig. 5.28. ASIC channels that fired together on a monolithic LYSO crystal

As expected we see that light reaches all pixels on the detector, which is what would be expected of a large monolithic crystal.

LYSO array 1.28 mm pitch Although we were not able to acquire a good spectrum with the larger monolithic crystal we had hopes for this LYSO array since according to our reasoning less light would in the end gives us better results.

After carefully adjusting the ASIC configuration, we obtained a spectrum that looked more like a ^{22}Na spectrum should look like. A good energy spectrum is an indicator of the proper functioning of the detector, crystal, acquisition system configuration.

Fig. 5.29. Energy spectrum using a squared pixel array with the TRIROC ASIC

In this spectrum we again see the same quanta for each activated channel on each event detected. The interesting aspect is that if we compare it to the result for the monolithic crystal we now see that there is a peak for the activation of 3 or 4 channels at the same time. We analyzed this data in more detail and realized that this was in fact related to the 511 keV photopeak. By keeping only those events where at least 4 channels have triggered we can clearly distinguish the 511 keV peak on the Low Gain energy spectrum.

Fig. 5.30. 511 keV photopeak on the Low Gain ASIC output

Considering that the events on the previous spectrum are the ones we would use on a PET acquisition for image generation, we can use only these events to generate a flood field image by combining the information from both ASIC outputs. To combine the outputs we use a weighted sum assigning more value to one or the other depending on how

many channels fired for each events, this helps by compensating for the distribution of light. When an event is distributed across several channels it will always be easier to position than when only a few channels have received enough light as to trigger a data conversion in the ASIC.

Fig. 5.31. Flood field image of a 1.3 mm pitch array

On this flood field image, the different pixels forming the array are clearly distinguishable from one another. This means that we can use this crystal, detector, ASIC combination in a PET detector. The images obtained for other energy ranges might not be as good as this one, but this is the energy spectrum of interest for PET studies, so it fits perfectly with our intended goals.

If we check as before which crystals fire together we can see that the light is spread far less than what it was on the monolithic crystals with only a few of the neighbouring pixels firing each time.

Fig. 5.32. ASIC channels that fired together on a 1.3 m pitch array

On this acquisition we saw a similar effect as what we had seen before with the High Gain values of the ASIC, just that in this case whenever there was a High Gain reading it always came along a Low Gain reading. Our thoughts on this is that for this crystals light is more focused thus all detector channels receiving light get enough of it as to generate a trigger signal in the ASIC.

We tried using the configuration that worked with the pixelated array with the monolithic crystal but got the same results we had before. We are still trying to find a solution to see whether or not it will be possible to use this ASIC with monolithic crystals but so far our results seem to indicate that it will not be possible. However, the results obtained with the pixelated array serves as proof that this ASIC could be used on a PET scanner built with pixelated arrays.

We did not test the large pixelated array with this ASIC since it would require a very long acquisition time and be very prone to failure because of that same reason, since the data acquisition application on the PC side is not very reliable.

5.4.6. ASIC vs Analog

Since we are considering two different design choices for our scanner we think it is a good idea to make a side by side comparison of the two results. Only the data obtained for the small pixelated array is presented here, since it is the solution closest to the configuration that would be present on our proposed scanner.

(a) Spatial resolution analog encoding

(b) Spatial resolution ASIC

Fig. 5.33. ASIC vs Analog encoding using a 1.3 mm squared array

The results leave no doubt that the ASIC configuration is far superior in terms of spatial resolution than the analog encoding scheme. Both however, present a good result and all pixels are resolvable in both approaches, so both options can be considered as valid for a future implementation, at least in terms of spatial resolution.

The main drawback with the ASIC remains on the maximum counts per second we can obtain when using it but we have reason to believe that this will be solved in the next iterations of this ASIC. If the manufacturers were to provide us with a new ASIC with similar physical characteristics it should be very easy to update just part of our design to accommodate the new ASIC and improve the count rate of our system ensuring like this the desired 400 thousand counts per second per scanner face.

6. CONCLUSIONS AND FUTURE LINES

All of the work here presented demonstrates that without a doubt SiPMs are a perfect candidate for the replacement of PMTs, as the detector element on radiation detectors for nuclear medicine applications. The energy and spatial resolution of the detectors presented in this work is comparable to that of commercial systems built using PMTs.

An electronic dosimeter was developed and used to test the use of SiPMs as radiation detectors. During the design process of this dosimeter we could assess that electronic designs used with PMTs were also valid with SiPMs. The electronic dosimeter proved able to acquire energy spectra in real time, providing localization information as well. From these energy spectra it is possible to identify the radiation isotopes that generate the radiation.

A SiPM based detector with enough energy and spatial resolution to be fit for a PET system was developed. With this detector we could clearly identify the pixels on a scintillator array with a pixel pitch of 1.38 mm, proving that this detector can be used to build a preclinical PET scanner. The energy resolution of this detector is 13.37, allowing a clear distinction of the 511 keV photons used in PET. We proved that these detectors can be used with SSLE arrays with the aid of a light guide.

Four detectors were built and assembled in an octagon ring shape to acquire tomographic PET images. With this detector configuration we reconstructed a point source of 1.3 mm placed in the center of the field of view, proving the tomographic capabilities of the system.

A novel PET scanner design, based on an icosahedron, with improved solid angle coverage has been proposed. The improvement in solid angle coverage implies an improvement in sensitivity and resolution as well. New detector and scintillator geometries have been used for this scanner in order to further enhance the resolution of the scanner.

A detector with an hexagonal shape was developed and tested using different scintillator arrays. The electronics required for multiplexing a detector with hexagonal pixel arrangement have given results as good as those obtained with conventional(squared) SiPM detectors. Pixels on a scintillator array with a pixel pitch of 1.28 mm were easily identified using analog multiplexing. A detector built using the TRIROC ASIC, instead of the conventional analog front end and data acquisition system combination, was developed and tested as well. The results obtained using this ASIC suggest that scintillator arrays with a pixel pitch of 1 mm, could also be resolved. This detector was also proven capable of resolving the pixels on a SSLE scintillator array.

6.1. What lies ahead

The prototype proposed in chapter 4, can be turned into a functioning scanner but for that a thorough characterization is necessary. The NEMA NU 4-2008 standard dictates the guidelines for measuring the performance of a small animal PET scanner. After making the necessary adjustment, mostly mechanical, a more robust detector ring can be constructed, with a bed that insert in the ring, and tested according to the NEMA standard. Once the scanner is fully characterized we can start small animal studies with this system.

We have enough confidence in our system as to say that if a company were to be interested in turning this into an actual product, the changes needed would be minor. Most of them on the user interface side, currently we use a console based interface to communicate with the scanner.

From a research perspective the work presented in chapter 5 is the most promising. The road ahead looks very good so far, but there is still plenty of work to be done. First we would need to improve the code used on the FPGA that controls the TRIROC ASIC to properly test the acquisition limits of this ASIC.

We have already been discussing about this with Weeroc, the company that manufactures the ASIC, and they offered to give us all the code in the FPGA so that we can modify it as we see fit. Next step will be to design our own PCB using the TRIROC, once these two milestones are achieved we can start building detectors, and from them, the faces of our icoPET.

With at least two fully working detector faces we could start experimenting to test our hypothesis regarding the improvements in sensitivity and resolution that we expect to see on the icoPET.

BIBLIOGRAPHY

- [1] V. Kontis *et al.*, “Future life expectancy in 35 industrialised countries: projections with a Bayesian model ensemble.”, *Lancet (London, England)*, vol. 389, no. 10076, pp. 1323–1335, 2017. doi: [10.1016/S0140-6736\(16\)32381-9](https://doi.org/10.1016/S0140-6736(16)32381-9). [Online]. Available: <http://www.ncbi.nlm.nih.gov/pubmed/28236464><http://www.pubmedcentral.nih.gov/articlerender.fcgi?artid=PMC5387671>.
- [2] G. P. Collaborators and Fertility, “Population and fertility by age and sex for 195 countries and territories, 1950–2017: a systematic analysis for the Global Burden of Disease Study 2017”, *Lancet (London, England)*, vol. 392, no. 10159, p. 1995, 2018. doi: [10.1016/S0140-6736\(18\)32278-5](https://doi.org/10.1016/S0140-6736(18)32278-5). [Online]. Available: <https://www.ncbi.nlm.nih.gov/pmc/articles/PMC6227915/>.
- [3] A. Y. Chang, V. F. Skirbekk, S. Tyrovolas, N. J. Kassebaum, and J. L. Dieleman, “Measuring population ageing: an analysis of the Global Burden of Disease Study 2017.”, *The Lancet. Public health*, vol. 4, no. 3, e159–e167, 2019. doi: [10.1016/S2468-2667\(19\)30019-2](https://doi.org/10.1016/S2468-2667(19)30019-2). [Online]. Available: <http://www.ncbi.nlm.nih.gov/pubmed/30851869><http://www.pubmedcentral.nih.gov/articlerender.fcgi?artid=PMC6472541>.
- [4] R. L. Siegel, K. D. Miller, and A. Jemal, “Cancer statistics, 2019”, *CA: A Cancer Journal for Clinicians*, vol. 69, no. 1, pp. 7–34, 2019. doi: [10.3322/caac.21551](https://doi.org/10.3322/caac.21551). [Online]. Available: <http://doi.wiley.com/10.3322/caac.21551>.
- [5] M. R. Bernsen *et al.*, “The role of preclinical SPECT in oncological and neurological research in combination with either CT or MRI”, *European Journal of Nuclear Medicine and Molecular Imaging*, vol. 41, no. S1, pp. 36–49, 2014. doi: [10.1007/s00259-013-2685-3](https://doi.org/10.1007/s00259-013-2685-3). [Online]. Available: <http://link.springer.com/10.1007/s00259-013-2685-3>.
- [6] P. M. Matthews *et al.*, “Technologies: preclinical imaging for drug development”, *Drug Discovery Today: Technologies*, vol. 10, no. 3, e343–e350, 2013. doi: [10.1016/J.DDTEC.2012.04.004](https://doi.org/10.1016/J.DDTEC.2012.04.004). [Online]. Available: <https://www.sciencedirect.com/science/article/pii/S174067491200025X?via=ihub>.
- [7] G. B. Saha, *Physics and radiobiology of nuclear medicine*. Springer, 2014.
- [8] R. A. Powsner, M. R. Palmer, and E. R. Powsner, *Essentials of nuclear medicine physics and instrumentation*. John Wiley & Sons, Ltd, 2013. [Online]. Available: <https://www.wiley.com/en-am/Essentials+of+Nuclear+Medicine+Physics+and+Instrumentation%2C+3rd+Edition-p-9780470905500>.

- [9] J. J. Vaquero and P. Kinahan, “Positron Emission Tomography: Current Challenges and Opportunities for Technological Advances in Clinical and Preclinical Imaging Systems.”, *Annual review of biomedical engineering*, vol. 17, pp. 385–414, 2015. doi: [10.1146/annurev-bioeng-071114-040723](https://doi.org/10.1146/annurev-bioeng-071114-040723). [Online]. Available: <http://www.ncbi.nlm.nih.gov/pubmed/26643024><http://www.pubmedcentral.nih.gov/articlerender.fcgi?artid=PMC5299095>.
- [10] S. R. Cherry, J. A. Sorenson, and M. E. Phelps, *Physics in nuclear medicine*. Elsevier/Saunders, 2012, p. 523. [Online]. Available: <https://www.sciencedirect.com/book/9781416051985/physics-in-nuclear-medicine>.
- [11] *Nuclear Medicine Physics*, ser. Non-serial Publications. Vienna: INTERNATIONAL ATOMIC ENERGY AGENCY, 2015. [Online]. Available: <https://www.iaea.org/publications/10368/nuclear-medicine-physics>.
- [12] *Radiation Protection and Safety of Radiation Sources: International Basic Safety Standards*, ser. General Safety Requirements GSR Part 3. Vienna: INTERNATIONAL ATOMIC ENERGY AGENCY, 2014. [Online]. Available: <https://www.iaea.org/publications/8930/radiation-protection-and-safety-of-radiation-sources-international-basic-safety-standards>.
- [13] “Scintillation Camera with Multichannel Collimators Hal 0. Anger1”, Tech. Rep. [Online]. Available: <http://jnm.snmjournals.org/content/5/7/515.full.pdf>.
- [14] G. F. Knoll, *Radiation detection and measurement*. John Wiley, 2010, p. 830. [Online]. Available: <https://www.wiley.com/en-bt/Radiation+Detection+and+Measurement%2C+4th+Edition-p-9780470131480>.
- [15] B. H. Peng and C. S. Levin, “Recent development in PET instrumentation.”, *Current pharmaceutical biotechnology*, vol. 11, no. 6, pp. 555–71, 2010. [Online]. Available: <http://www.ncbi.nlm.nih.gov/pubmed/20497121><http://www.pubmedcentral.nih.gov/articlerender.fcgi?artid=PMC3697478>.
- [16] Saint-Gobain Crystals, “Scintillation Materials and Assemblies”, Saint-Gobain Crystals, Tech. Rep. [Online]. Available: www.crystals.saint-gobain.com.
- [17] K Sato, Y Enomoto, and Y Adachi, “A technical guide to silicon photomultipliers (MPPC)”, Tech. Rep., 2018, pp. 1–65. [Online]. Available: <https://hub.hamamatsu.com/us/en/technical-note/sipm-mppc-technical-note/index.html>.
- [18] T. Hakamata, “PHOTOMULTIPLIER TUBES Basics and Applications THIRD EDITION (Edition 3a)”, Tech. Rep., 2007. [Online]. Available: <https://www.hamamatsu.com/resources/pdf/etd/PMT%5C%2F%5C%2Fhandbook%5C%2Fv3aE.pdf>.
- [19] SensL, “An Introduction to the Silicon Photomultiplier”, Tech. Rep., 2011, pp. 1–8. [Online]. Available: www.onsemi.com.

- [20] W. W. Moses, “Fundamental Limits of Spatial Resolution in PET.”, *Nuclear instruments & methods in physics research. Section A, Accelerators, spectrometers, detectors and associated equipment*, vol. 648 Supple, S236–S240, 2011. doi: [10.1016/j.nima.2010.11.092](https://doi.org/10.1016/j.nima.2010.11.092). [Online]. Available: <http://www.ncbi.nlm.nih.gov/pubmed/21804677><http://www.pubmedcentral.nih.gov/articlerender.fcgi?artid=PMC3144741>.
- [21] M. Defrise, P. E. Kinahan, and C. J. Michel, “Image Reconstruction Algorithms in PET”, in *Positron Emission Tomography*, London: Springer-Verlag, 2005, pp. 63–91. doi: [10.1007/1-84628-007-9_4](https://doi.org/10.1007/1-84628-007-9_4). [Online]. Available: http://link.springer.com/10.1007/1-84628-007-9_{_}4.
- [22] G. Kontaxakis *et al.*, “Iterative image reconstruction for clinical PET using ordered subsets, median root prior, and a web-based interface.”, *Molecular imaging and biology : MIB : the official publication of the Academy of Molecular Imaging*, vol. 4, no. 3, pp. 219–31, 2002. [Online]. Available: <http://www.ncbi.nlm.nih.gov/pubmed/14537126>.
- [23] G. T. Herman, *Fundamentals of Computerized Tomography Image Reconstruction from Projections*. Springer-Verlag New York Inc, 2012.
- [24] M. Ahmad and A. Todd-Pokropek, *Tomographic image reconstruction and quantification for PET/SPECT : non-uniform resolution and partial volume recovery methods*. VDM, 2009.
- [25] J. Vaquero *et al.*, “Design of DOI PET detector modules using phoswich and SiPMs: First results”, in *2011 IEEE Nuclear Science Symposium Conference Record*, IEEE, 2011, pp. 3311–3313. doi: [10.1109/NSSMIC.2011.6152597](https://doi.org/10.1109/NSSMIC.2011.6152597). [Online]. Available: <http://ieeexplore.ieee.org/document/6152597/>.
- [26] “Directiva 2013/59/Euratom del Consejo, de 5 de diciembre de 2013, por la que se establecen normas de seguridad básicas para la protección contra los peligros derivados de la exposición a radiaciones ionizantes, y se derogan las Directivas 89/618/Euratom, 90/641/Euratom, 96/29/Euratom, 97/43/Euratom y 2003/122/Euratom”, Tech. Rep. [Online]. Available: <https://www.csn.es/documents/10182/27584/Directiva2013-59-EURATOM,delConsejo,de5dediciembrede2013,porlaqueseestablecennormasdeseguridadb{\'}{a}}sicaspalaprotecci{\'}{o}}ncontralospeligrosderivadosdelaexposici{\'}{o}}naradiacionesionizantes,ysederoganotrasDirectivas>.
- [27] M. Müller *et al.*, “Real-time dosimetry reduces radiation exposure of orthopaedic surgeons”, *Orthopaedics & Traumatology: Surgery & Research*, vol. 100, no. 8, pp. 947–951, 2014. doi: [10.1016/j.otsr.2014.09.016](https://doi.org/10.1016/j.otsr.2014.09.016). [Online]. Available: <https://linkinghub.elsevier.com/retrieve/pii/S187705681400259X>.

- [28] S. Poudel, L. Weir, D. Dowling, and D. C. Medich, “Changes in Occupational Radiation Exposures after Incorporation of a Real-time Dosimetry System in the Interventional Radiology Suite”, *Health Physics*, vol. 111, S166–S171, 2016. doi: [10.1097/HP.0000000000000546](https://doi.org/10.1097/HP.0000000000000546). [Online]. Available: <https://insights.ovid.com/crossref?an=00004032-201608002-00007>.
- [29] *Real-time staff dose radiation monitoring: Immediate and long-term solutions for reducing medical radiation risks | Fluke Biomedical*. [Online]. Available: <https://www.flukebiomedical.com/resource/i3-whitepaper-real-time-staff-dose-radiation-monitoring> (visited on 04/08/2019).
- [30] Philips, *Specifications, DoseAware Radiation Dose Tracker, Philips*. [Online]. Available: <https://www.philips.com.au/healthcare/product/HC722360/doseaware-radiation-dose-tracker/specifications> (visited on 04/08/2019).
- [31] Mirion, “instadose dosimeters Dosimetry Services Division”, Tech. Rep. [Online]. Available: www.instadose.com.
- [32] “Handheld Detection for Any Scenario RadEye Selection Guide RadEye Product Family”, Tech. Rep., 2012. [Online]. Available: <https://assets.thermofisher.com/TFS-Assets/LSG/brochures/D16620{~}.pdf>.
- [33] Laurus, “identiFINDER R300 - nanoRAIDER - Spectroscopic Pager for Radiation Detection& Identification”, Tech. Rep. [Online]. Available: http://www.laurussystems.com/products/products{_}.pdf/LS-FLIR{_}identiFINDER-R300-nanoRAIDER.pdf.
- [34] “Clear Indication of Exposure Electronic Personal Dosimeter Real-Time Alarm Audible, visual, and vibrating alerts Pager-Like Design”, Tech. Rep. [Online]. Available: www.x-zlab.com.
- [35] “TRACERCO TM Monitors and Servicing TRACERCO TM PED: Personal Dosimeter”, Tech. Rep. [Online]. Available: www.tracerco.com/monitors.
- [36] “EPD Mk2+ Specifications”, Tech. Rep., 2009. [Online]. Available: www.thermo.com/rmp.
- [37] Mirion, “RAD-60/62 | Electronic Dosimeters”, Tech. Rep., 2014. [Online]. Available: www.mirion.com.
- [38] J. Ebenezer and S. A.V. S. Murty, “Deployment of Wireless Sensor Network for Radiation Monitoring”, pp. 27–32, 2015.
- [39] N. J. Jevtic and V. R. Drndarevic, “Smart sensors for environmental radiation monitoring networks”, in *2015 23rd Telecommunications Forum Telfor (TELFOR)*, IEEE, 2015, pp. 607–614. doi: [10.1109/TELFOR.2015.7377541](https://doi.org/10.1109/TELFOR.2015.7377541). [Online]. Available: <http://ieeexplore.ieee.org/document/7377541/>.

- [40] Y. Sanada and T. Torii, “Aerial radiation monitoring around the Fukushima Dai-ichi nuclear power plant using an unmanned helicopter”, *Journal of Environmental Radioactivity*, vol. 139, pp. 294–299, 2015. doi: [10.1016/j.jenvrad.2014.06.027](https://doi.org/10.1016/j.jenvrad.2014.06.027). [Online]. Available: <http://dx.doi.org/10.1016/j.jenvrad.2014.06.027>.
- [41] E. P. Sandi, “Mejoras e la deteccion de rayos gamma con cristales centelladores de última generación y aplicaciones”, PhD thesis, Universidad Complutense de Madrid, 2013.
- [42] L. M. Fraile *et al.*, “Nuevas tecnologías de detección para dosímetros individuales y en red”, Tech. Rep., 2011.
- [43] PHOTONIS |. [Online]. Available: <https://www.photonis.com/> (visited on 04/08/2019).
- [44] Hamamatsu, “MPPC ® (multi-pixel photon counter) - S10984/S10985 Series”, Tech. Rep., 2010. [Online]. Available: www.hamamatsu.com.
- [45] SensL, *SensL – Silicon Photomultipliers & SPADs*. [Online]. Available: <https://sensl.com/> (visited on 04/08/2019).
- [46] R Chil, L. M. Fraile, J Vaquero, and E Picado, “XIII Mediterranean Conference on Medical and Biological Engineering and Computing 2013”, vol. 41, 2014. doi: [10.1007/978-3-319-00846-2](https://doi.org/10.1007/978-3-319-00846-2). [Online]. Available: <http://link.springer.com/10.1007/978-3-319-00846-2>.
- [47] R. Chil, G. Konstantinou, M. Desco, and J. J. Vaquero, “Highly multiplexed DOI PET detector based on SiPM sensors”, in *2015 IEEE Nuclear Science Symposium and Medical Imaging Conference (NSS/MIC)*, IEEE, 2015, pp. 1–3. doi: [10.1109/NSSMIC.2015.7582150](https://doi.org/10.1109/NSSMIC.2015.7582150). [Online]. Available: <http://ieeexplore.ieee.org/document/7582150/>.
- [48] R. Chil, G. Konstantinou, M. Desco, and J. Vaquero, “Compact, MR compatible SiPM small animal PET DOI detector”, in *2016 IEEE Nuclear Science Symposium, Medical Imaging Conference and Room-Temperature Semiconductor Detector Workshop (NSS/MIC/RTSD)*, IEEE, 2016, pp. 1–2. doi: [10.1109/NSSMIC.2016.8069413](https://doi.org/10.1109/NSSMIC.2016.8069413). [Online]. Available: <https://ieeexplore.ieee.org/document/8069413/>.
- [49] SensL, “Biasing and Readout of SensL SiPM Sensors”, Tech. Rep. [Online]. Available: https://sensl.com/downloads/ds/TN-Biasing{_}and{_}Readout.pdf.
- [50] A Ghassemi *et al.*, “Hamamatsu MPPC Technical Note”, Tech. Rep., 2018. [Online]. Available: https://hub.hamamatsu.com/sp/hc/resources/TN0014/mppc{_}kapd9005e.pdf.

- [51] S. Gundacker *et al.*, “A Systematic Study to Optimize SiPM Photo-Detectors for Highest Time Resolution in PET”, *IEEE Transactions on Nuclear Science*, vol. 59, no. 5, pp. 1798–1804, 2012. doi: [10.1109/TNS.2012.2202918](https://doi.org/10.1109/TNS.2012.2202918). [Online]. Available: <http://ieeexplore.ieee.org/document/6236267/>.
- [52] H. Anger, “Scintillation Camera with Multichannel Collimators Hal 0. Anger1”, Tech. Rep. [Online]. Available: <http://jnm.snmjournals.org/content/5/7/515.full.pdf>.
- [53] A. J. Chaudhari *et al.*, “Spatial distortion correction and crystal identification for MRI-compatible position-sensitive avalanche photodiode-based PET scanners.”, *IEEE transactions on nuclear science*, vol. 56, no. 3, pp. 549–556, 2009. doi: [10.1109/TNS.2009.2018841](https://doi.org/10.1109/TNS.2009.2018841). [Online]. Available: <http://www.ncbi.nlm.nih.gov/pubmed/20161023http://www.pubmedcentral.nih.gov/articlerender.fcgi?artid=PMC2749315>.
- [54] Xishan Sun, Kai Lou, and Yiping Shao, “Capacitor based multiplexing circuit for silicon photomultiplier array readout”, in *2014 IEEE Nuclear Science Symposium and Medical Imaging Conference (NSS/MIC)*, IEEE, 2014, pp. 1–5. doi: [10.1109/NSSMIC.2014.7431219](https://doi.org/10.1109/NSSMIC.2014.7431219). [Online]. Available: <http://ieeexplore.ieee.org/document/7431219/>.
- [55] H.-J. Choe, Y. Choi, W. Hu, J. Yan, and J. Ho Jung, “Development of capacitive multiplexing circuit for SiPM-based time-of-flight (TOF) PET detector”, *Physics in Medicine and Biology*, vol. 62, no. 7, N120–N133, 2017. doi: [10.1088/1361-6560/aa5f9b](https://doi.org/10.1088/1361-6560/aa5f9b). [Online]. Available: <http://stacks.iop.org/0031-9155/62/i=7/a=N120?key=crossref.a70b73b9a40b5d93d199c62b7805d80a>.
- [56] D. Stratos, G. Maria, F. Eleftherios, and L. George, “Comparison of three resistor network division circuits for the readout of 44 pixel SiPM arrays”, *Nuclear Instruments and Methods in Physics Research Section A: Accelerators, Spectrometers, Detectors and Associated Equipment*, vol. 702, pp. 121–125, 2013. doi: [10.1016/j.nima.2012.08.006](https://doi.org/10.1016/j.nima.2012.08.006). [Online]. Available: <http://linkinghub.elsevier.com/retrieve/pii/S0168900212008583>.
- [57] A. L. Goertzen *et al.*, “Design and Performance of a Resistor Multiplexing Readout Circuit for a SiPM Detector”, vol. 60, no. 3, pp. 1541–1549, 2013.
- [58] V. Popov, S. Majewski, and A. Weisenberger, “Readout electronics for multianode photomultiplier tubes with pad matrix anode layout”, in *2003 IEEE Nuclear Science Symposium. Conference Record (IEEE Cat. No.03CH37515)*, IEEE, 2003, 2156–2159 Vol.3. doi: [10.1109/NSSMIC.2003.1352307](https://doi.org/10.1109/NSSMIC.2003.1352307). [Online]. Available: <http://ieeexplore.ieee.org/document/1352307/>.
- [59] J. Y. Won and J. S. Lee, “Highly Integrated FPGA-Only Signal Digitization Method Using Single-Ended Memory Interface Input Receivers for Time-of-Flight PET Detectors”, *IEEE Transactions on Biomedical Circuits and Systems*, vol. 12, no. 6,

- J.NIMA.2010.07.008. [Online]. Available: <https://www.sciencedirect.com/science/article/pii/S0168900210015500>.
- [69] “J-Series High PDE and Timing Resolution, TSV Package”, Tech. Rep., 2017. [Online]. Available: <https://sensl.com/downloads/ds/DS-MicroJseries.pdf>.
- [70] Nutaq, *PicoDigitizer 125-Series* | Nutaq. [Online]. Available: <https://www.nutaq.com/products/picodigitizer-125-series> (visited on 06/07/2019).
- [71] A. Corporation, “Cyclone II Device Handbook”, Tech. Rep., 2008. [Online]. Available: www.altera.com.
- [72] E. Sources, *Spot Markers - Epsilon Radioactive Sources*. [Online]. Available: <http://www.epsilon-sources.com/spot-markers/> (visited on 05/30/2019).
- [73] G. Konstantinou *et al.*, “Simulations, testing and results for the pixelation of LYSO crystals for gamma detectors using SSLE techniques”, in *2014 IEEE Nuclear Science Symposium and Medical Imaging Conference (NSS/MIC)*, IEEE, 2014, pp. 1–4. doi: [10.1109/NSSMIC.2014.7430866](https://doi.org/10.1109/NSSMIC.2014.7430866). [Online]. Available: <http://ieeexplore.ieee.org/document/7430866/>.
- [74] G. Konstantinou, R. Chil, M. Desco, and J. J. Vaquero, “Applications of sub-surface laser engraving on monolithic scintillator crystals: Novel pixel geometries and depth of interaction”, in *2016 IEEE Nuclear Science Symposium, Medical Imaging Conference and Room-Temperature Semiconductor Detector Workshop (NSS/MIC/RTSD)*, IEEE, 2016, pp. 1–4. doi: [10.1109/NSSMIC.2016.8069805](https://doi.org/10.1109/NSSMIC.2016.8069805). [Online]. Available: <https://ieeexplore.ieee.org/document/8069805/>.
- [75] —, “Subsurface Laser Engraving Techniques for Scintillator Crystals: Methods, Applications, and Advantages”, *IEEE Transactions on Radiation and Plasma Medical Sciences*, vol. 1, no. 5, pp. 377–384, 2017. doi: [10.1109/TRPMS.2017.2714265](https://doi.org/10.1109/TRPMS.2017.2714265). [Online]. Available: <http://ieeexplore.ieee.org/document/7945285/>.
- [76] G. Konstantinou, J. J. Vaquero López, R. Chil Pérez, and M. Desco Menéndez, *Celda centelleadora*, 2016. [Online]. Available: <https://patents.google.com/patent/ES2665888B1/es?inventor=Rigoberto+CHIL+P{\'\{E\}}REZ>.
- [77] S. R. Cherry *et al.*, “Total-body imaging: Transforming the role of positron emission tomography.”, *Science translational medicine*, vol. 9, no. 381, 2017. doi: [10.1126/scitranslmed.aaf6169](https://doi.org/10.1126/scitranslmed.aaf6169). [Online]. Available: <http://www.ncbi.nlm.nih.gov/pubmed/28298419http://www.pubmedcentral.nih.gov/articlerender.fcgi?artid=PMC5629037>.
- [78] Z. Cho, K. Hong, and S. Hilal, “Spherical positron emission tomograph (S-PET) I - performance analysis”, *Nuclear Instruments and Methods in Physics Research*, vol. 225, no. 2, pp. 422–438, 1984. doi: [10.1016/0167-5087\(84\)90282-5](https://doi.org/10.1016/0167-5087(84)90282-5). [Online]. Available: <https://www.sciencedirect.com/science/article/pii/0167508784902825?via{\%}3Dihub>.

- [79] T. Jones and D. Townsend, “History and future technical innovation in positron emission tomography.”, *Journal of medical imaging (Bellingham, Wash.)*, vol. 4, no. 1, p. 011 013, 2017. doi: [10.1117/1.JMI.4.1.011013](https://doi.org/10.1117/1.JMI.4.1.011013). [Online]. Available: <http://www.ncbi.nlm.nih.gov/pubmed/28401173><http://www.pubmedcentral.nih.gov/articlerender.fcgi?artid=PMC5374360>.
- [80] J. K. Poon *et al.*, “Optimal whole-body PET scanner configurations for different volumes of LSO scintillator: a simulation study”, *Physics in Medicine and Biology*, vol. 57, no. 13, pp. 4077–4094, 2012. doi: [10.1088/0031-9155/57/13/4077](https://doi.org/10.1088/0031-9155/57/13/4077). [Online]. Available: <http://stacks.iop.org/0031-9155/57/i=13/a=4077?key=crossref.d19f6c838d67dca21cc5056a2b30c4da>.
- [81] S. R. Cherry *et al.*, “Total-Body PET: Maximizing Sensitivity to Create New Opportunities for Clinical Research and Patient Care.”, *Journal of nuclear medicine : official publication, Society of Nuclear Medicine*, vol. 59, no. 1, pp. 3–12, 2018. doi: [10.2967/jnumed.116.184028](https://doi.org/10.2967/jnumed.116.184028). [Online]. Available: <http://www.ncbi.nlm.nih.gov/pubmed/28935835><http://www.pubmedcentral.nih.gov/articlerender.fcgi?artid=PMC5750522>.
- [82] R. D. Badawi *et al.*, “First Human Imaging Studies with the EXPLORER Total-Body PET Scanner.”, *Journal of nuclear medicine : official publication, Society of Nuclear Medicine*, vol. 60, no. 3, pp. 299–303, 2019. doi: [10.2967/jnumed.119.226498](https://doi.org/10.2967/jnumed.119.226498). [Online]. Available: <http://www.ncbi.nlm.nih.gov/pubmed/30733314><http://www.pubmedcentral.nih.gov/articlerender.fcgi?artid=PMC6424228>.
- [83] E. Berg and S. R. Cherry, “Innovations in Instrumentation for Positron Emission Tomography”, *Seminars in Nuclear Medicine*, vol. 48, no. 4, pp. 311–331, 2018. doi: [10.1053/J.SEMNUCLMED.2018.02.006](https://doi.org/10.1053/J.SEMNUCLMED.2018.02.006). [Online]. Available: <https://www.sciencedirect.com/science/article/pii/S000129981830014X?via=ihub>.
- [84] W. W. Moses, “Fundamental Limits of Spatial Resolution in PET.”, *Nuclear instruments & methods in physics research. Section A, Accelerators, spectrometers, detectors and associated equipment*, vol. 648 Supple, S236–S240, 2011. doi: [10.1016/j.nima.2010.11.092](https://doi.org/10.1016/j.nima.2010.11.092). [Online]. Available: <http://www.ncbi.nlm.nih.gov/pubmed/21804677><http://www.pubmedcentral.nih.gov/articlerender.fcgi?artid=PMC3144741>.
- [85] Wikipedia contributors, *Platonic solid — Wikipedia, the free encyclopedia*, [Online; accessed 10-June-2019], 2019. [Online]. Available: https://en.wikipedia.org/w/index.php?title=Platonic_solid&oldid=899827216.
- [86] —, *Archimedean solid — Wikipedia, the free encyclopedia*, [Online; accessed 10-June-2019], 2019. [Online]. Available: https://en.wikipedia.org/w/index.php?title=Archimedean_solid&oldid=890882029.

- [87] H. Shi, D. Du, J. Xu, Z. Su, and Q. Peng, “Design study of dedicated brain PET with polyhedron geometry”, *Technology and Health Care*, vol. 23, no. s2, E. J. Ciaccio, Ed., S615–S623, 2015. doi: [10.3233/THC-151000](https://doi.org/10.3233/THC-151000). [Online]. Available: <http://www.medra.org/servlet/aliasResolver?alias=iospress&doi=10.3233/THC-151000>.
- [88] D. Hellfeld, P. Barton, D. Gunter, L. Mihailescu, and K. Vetter, “A Spherical Active Coded Aperture for \$4\$ Gamma-Ray Imaging”, *IEEE Transactions on Nuclear Science*, vol. 64, no. 11, pp. 2837–2842, 2017. doi: [10.1109/TNS.2017.2755982](https://doi.org/10.1109/TNS.2017.2755982). [Online]. Available: <http://ieeexplore.ieee.org/document/8048531/>.
- [89] Wikipedia contributors, *Icosahedron — Wikipedia, the free encyclopedia*, [Online; accessed 30-May-2019], 2019. [Online]. Available: <https://en.wikipedia.org/w/index.php?title=Icosahedron&oldid=896851976>.
- [90] —, *Bacteriophage — Wikipedia, the free encyclopedia*, [Online; accessed 30-May-2019], 2019. [Online]. Available: <https://en.wikipedia.org/w/index.php?title=Bacteriophage&oldid=896131204>.
- [91] —, *Euclidean tilings by convex regular polygons — Wikipedia, the free encyclopedia*, [Online; accessed 31-May-2019], 2019. [Online]. Available: https://en.wikipedia.org/w/index.php?title=Euclidean_tilings_by_convex_regular_polygons&oldid=897192536.
- [92] “Scintillation Camera with Multichannel Collimators Hal 0. Anger1”, Tech. Rep. [Online]. Available: <http://jnm.snmjournals.org/content/5/7/515.full.pdf>.
- [93] G. Konstantinou, “Application of novel technologies for the development of next generation MR compatible PET inserts”, PhD thesis, 2017. [Online]. Available: <https://e-archivo.uc3m.es/handle/10016/25224>.
- [94] G. Konstantinou, R. Chil, M. Desco, and J. J. Vaquero, “Subsurface Laser Engraving Techniques for Scintillator Crystals: Methods, Applications, and Advantages”, *IEEE Transactions on Radiation and Plasma Medical Sciences*, vol. 1, no. 5, pp. 377–384, 2017. doi: [10.1109/TRPMS.2017.2714265](https://doi.org/10.1109/TRPMS.2017.2714265). [Online]. Available: <http://ieeexplore.ieee.org/document/7945285/>.
- [95] A. Del Guerra *et al.*, “TRIMAGE: A dedicated trimodality (PET/MR/EEG) imaging tool for schizophrenia”, *European Psychiatry*, vol. 50, pp. 7–20, 2018. doi: [10.1016/j.eurpsy.2017.11.007](https://doi.org/10.1016/j.eurpsy.2017.11.007). [Online]. Available: <https://www.sciencedirect.com/science/article/pii/S0924933817330134?via=ihub>.
- [96] J. M. Benlloch *et al.*, “The MINDVIEW project: First results”, *European Psychiatry*, vol. 50, pp. 21–27, 2018. doi: [10.1016/j.eurpsy.2018.01.002](https://doi.org/10.1016/j.eurpsy.2018.01.002). [Online]. Available: <https://www.sciencedirect.com/science/article/pii/S0924933818300026>.

- [97] C. Nanni, S. Fanti, and D. Rubello, “¹⁸F-DOPA PET and PET/CT.”, *Journal of nuclear medicine : official publication, Society of Nuclear Medicine*, vol. 48, no. 10, pp. 1577–9, 2007. doi: [10.2967/jnumed.107.041947](https://doi.org/10.2967/jnumed.107.041947). [Online]. Available: <http://www.ncbi.nlm.nih.gov/pubmed/17909255>.
- [98] O. D. Howes *et al.*, “The Nature of Dopamine Dysfunction in Schizophrenia and What This Means for Treatment”, *Archives of General Psychiatry*, vol. 69, no. 8, 2012. doi: [10.1001/archgenpsychiatry.2012.169](https://doi.org/10.1001/archgenpsychiatry.2012.169). [Online]. Available: <http://archpsyc.jamanetwork.com/article.aspx?doi=10.1001/archgenpsychiatry.2012.169>.
- [99] S. R. Cherry, “The 2006 Henry N. Wagner Lecture: Of mice and men (and positrons)—advances in PET imaging technology.”, *Journal of nuclear medicine : official publication, Society of Nuclear Medicine*, vol. 47, no. 11, pp. 1735–45, 2006. [Online]. Available: <http://www.ncbi.nlm.nih.gov/pubmed/17079804>.
- [100] G. Konstantinou, R. Chil, M. Desco, and J. J. Vaquero, “Applications of sub-surface laser engraving on monolithic scintillator crystals: Novel pixel geometries and depth of interaction”, in *2016 IEEE Nuclear Science Symposium, Medical Imaging Conference and Room-Temperature Semiconductor Detector Workshop (NSS/MIC/RTSD)*, IEEE, 2016, pp. 1–4. doi: [10.1109/NSSMIC.2016.8069805](https://doi.org/10.1109/NSSMIC.2016.8069805). [Online]. Available: <https://ieeexplore.ieee.org/document/8069805/>.
- [101] S. Paonessa, S. Di Pascoli, E. Balaban, and J. J. Vaquero, “Design and development of a wireless infrared EEG recorder for chicken embryos”, in *2016 IEEE International Symposium on Medical Measurements and Applications (MeMeA)*, IEEE, 2016, pp. 1–6. doi: [10.1109/MeMeA.2016.7533785](https://doi.org/10.1109/MeMeA.2016.7533785). [Online]. Available: <http://ieeexplore.ieee.org/document/7533785/>.
- [102] D. Perez-Benito *et al.*, “Proposal for a PET scanner with 4π formula steradian span”, in *2017 IEEE Nuclear Science Symposium and Medical Imaging Conference (NSS/MIC)*, IEEE, 2017, pp. 1–4. doi: [10.1109/NSSMIC.2017.8532648](https://doi.org/10.1109/NSSMIC.2017.8532648). [Online]. Available: <https://ieeexplore.ieee.org/document/8532648/>.
- [103] *IEEE 2018 NSS/MIC/RTSD Online Program*. [Online]. Available: https://www.eventclass.org/contxt{_}ieee2018/online-program/session?s=M-03 (visited on 05/28/2019).
- [104] “Abstracts of the Total Body PET conference 2018 : Ghent, Belgium. 30 June - 2 July 2018.”, *EJNMMI physics*, vol. 5, no. Suppl 1, p. 19, 2018. doi: [10.1186/s40658-018-0218-7](https://doi.org/10.1186/s40658-018-0218-7). [Online]. Available: <http://www.ncbi.nlm.nih.gov/pubmed/29956037http://www.pubmedcentral.nih.gov/articlerender.fcgi?artid=PMC6023806>.
- [105] D. Perez-Benito, R. Chil, J. Udias, M. Desco, and J. Vaquero, “Sipm-based pet detector module for a 4 span scanner”, *Nuclear Instruments and Methods in Physics Research Section A: Accelerators, Spectrometers, Detectors and Associated Equipment*, 2018. doi: <https://doi.org/10.1016/j.nima.2018.10.179>. [On-

- line]. Available: <http://www.sciencedirect.com/science/article/pii/S0168900218314931>.
- [106] V. Boccone *et al.*, “Characterization of new hexagonal large area geiger avalanche photodiodes”, in *2013 3rd International Conference on Advancements in Nuclear Instrumentation, Measurement Methods and their Applications (ANIMMA)*, IEEE, 2013, pp. 1–6. doi: [10.1109/ANIMMA.2013.6728058](https://doi.org/10.1109/ANIMMA.2013.6728058). [Online]. Available: <http://ieeexplore.ieee.org/document/6728058/>.
 - [107] J. Aguilar *et al.*, “The front-end electronics and slow control of large area SiPM for the SST-1M camera developed for the CTA experiment”, *Nuclear Instruments and Methods in Physics Research Section A: Accelerators, Spectrometers, Detectors and Associated Equipment*, vol. 830, pp. 219–232, 2016. doi: [10.1016/j.nima.2016.05.086](https://doi.org/10.1016/j.nima.2016.05.086). [Online]. Available: <https://linkinghub.elsevier.com/retrieve/pii/S0168900216304788>.
 - [108] M Heller *et al.*, “An innovative silicon photomultiplier digitizing camera for gamma-ray astronomy”, *Eur. Phys. J. C*, vol. 77, p. 47, 2017. doi: [10.1140/epjc/s10052-017-4609-z](https://doi.org/10.1140/epjc/s10052-017-4609-z). [Online]. Available: <https://link.springer.com/content/pdf/10.1140/epjc/s10052-017-4609-z.pdf>.
 - [109] M. Heller, “The single mirror small size telescope camera for the Cherenkov Telescope Array”, *Nuclear Instruments and Methods in Physics Research Section A: Accelerators, Spectrometers, Detectors and Associated Equipment*, vol. 787, pp. 182–184, 2015. doi: [10.1016/j.nima.2014.11.096](https://doi.org/10.1016/j.nima.2014.11.096). [Online]. Available: <https://linkinghub.elsevier.com/retrieve/pii/S0168900214014107>.
 - [110] S. Majewski, J. Proffitt, A. Stolin, and R. Raylman, “Development of a “resistive” readout for SiPM arrays”, in *2011 IEEE Nuclear Science Symposium Conference Record*, IEEE, 2011, pp. 3939–3944. doi: [10.1109/NSSMIC.2011.6153749](https://doi.org/10.1109/NSSMIC.2011.6153749). [Online]. Available: <http://ieeexplore.ieee.org/document/6153749/>.
 - [111] D. Stratos, G. Maria, F. Eleftherios, and L. George, “Comparison of three resistor network division circuits for the readout of 44 pixel SiPM arrays”, *Nuclear Instruments and Methods in Physics Research Section A: Accelerators, Spectrometers, Detectors and Associated Equipment*, vol. 702, pp. 121–125, 2013. doi: [10.1016/j.nima.2012.08.006](https://doi.org/10.1016/j.nima.2012.08.006). [Online]. Available: <http://linkinghub.elsevier.com/retrieve/pii/S0168900212008583>.
 - [112] A. L. Goertzen *et al.*, “Design and Performance of a Resistor Multiplexing Readout Circuit for a SiPM Detector”, vol. 60, no. 3, pp. 1541–1549, 2013.
 - [113] M. F. Bieniosek, J. W. Cates, and C. S. Levin, “A multiplexed TOF and DOI capable PET detector using a binary position sensitive network”, *Physics in Medicine and Biology*, vol. 61, no. 21, pp. 7639–7651, 2016. doi: [10.1088/0031-9155/61/21/7639](https://doi.org/10.1088/0031-9155/61/21/7639). [Online]. Available: <http://stacks.iop.org/0031-9155/61/i=21/a=7639?key=crossref.119ce278bc4018fd97620baba658c4c9>.

- [114] J. W. Cates, M. F. Bieniosek, and C. S. Levin, “Highly multiplexed signal readout for a time-of-flight positron emission tomography detector based on silicon photomultipliers.”, *Journal of medical imaging (Bellingham, Wash.)*, vol. 4, no. 1, p. 011 012, 2017. doi: [10 . 1117 / 1 . JMI . 4 . 1 . 011012](https://doi.org/10.1117/1.JMI.4.1.011012). [Online]. Available: [http : / / www . ncbi . nlm . nih . gov / pubmed / 28382312](http://www.ncbi.nlm.nih.gov/pubmed/28382312)[http : / / www . pubmedcentral . nih . gov / articlerender . fcgi ? artid = PMC5363788](http://www.pubmedcentral.nih.gov/articlerender.fcgi?artid=PMC5363788).
- [115] J. Y. Won and J. S. Lee, “Highly Integrated FPGA-Only Signal Digitization Method Using Single-Ended Memory Interface Input Receivers for Time-of-Flight PET Detectors”, *IEEE Transactions on Biomedical Circuits and Systems*, vol. 12, no. 6, pp. 1401–1409, 2018. doi: [10 . 1109 / TBCAS . 2018 . 2865581](https://doi.org/10.1109/TBCAS.2018.2865581). [Online]. Available: <https://ieeexplore.ieee.org/document/8437139/>.
- [116] S. Ahmad *et al.*, “Triroc: A Multi-Channel SiPM Read-Out ASIC for PET/PET-ToF Application”, *IEEE Transactions on Nuclear Science*, vol. 62, no. 3, pp. 664–668, 2015. doi: [10 . 1109 / TNS . 2015 . 2397973](https://doi.org/10.1109/TNS.2015.2397973). [Online]. Available: [http : / / ieeexplore . ieee . org / document / 7064797 /](http://ieeexplore.ieee.org/document/7064797/).
- [117] J. Barrio *et al.*, “Performance of VATA64HDR16 ASIC for medical physics applications based on continuous crystals and SiPMs”, *Journal of Instrumentation*, vol. 10, no. 12, P12001–P12001, 2015. doi: [10 . 1088 / 1748 - 0221 / 10 / 12 / P12001](https://doi.org/10.1088/1748-0221/10/12/P12001). [Online]. Available: [http : / / stacks . iop . org / 1748 - 0221 / 10 / i = 12 / a = P12001 ? key = crossref . f6afb33b99875ac947736548e522e139](http://stacks.iop.org/1748-0221/10/i=12/a=P12001?key=crossref.f6afb33b99875ac947736548e522e139).
- [118] J. M. Cela *et al.*, “Performance of the FlexToT v2 ASIC on the readout of different detector designs for PET”, in *2015 IEEE Nuclear Science Symposium and Medical Imaging Conference (NSS/MIC)*, IEEE, 2015, pp. 1–2. doi: [10 . 1109 / NSSMIC . 2015 . 7582141](https://doi.org/10.1109/NSSMIC.2015.7582141). [Online]. Available: [http : / / ieeexplore . ieee . org / document / 7582141 /](http://ieeexplore.ieee.org/document/7582141/).
- [119] W. Yonggang, C. Xinyi, L. Deng, Z. Wensong, and L. Chong, “A Linear Time-Over-Threshold Digitizing Scheme and Its 64-channel DAQ Prototype Design on FPGA for a Continuous Crystal PET Detector”, *IEEE Transactions on Nuclear Science*, vol. 61, no. 1, pp. 99–106, 2014. doi: [10 . 1109 / TNS . 2013 . 2293758](https://doi.org/10.1109/TNS.2013.2293758). [Online]. Available: [http : / / ieeexplore . ieee . org / document / 6710205 /](http://ieeexplore.ieee.org/document/6710205/).
- [120] X. Zhu, Z. Deng, Y. Chen, Y. Liu, and Y. Liu, “Development of a 64-Channel Readout ASIC for an SSPM Array for PET and TOF-PET Applications”, *IEEE Transactions on Nuclear Science*, pp. 1–8, 2016. doi: [10 . 1109 / TNS . 2016 . 2518808](https://doi.org/10.1109/TNS.2016.2518808). [Online]. Available: [http : / / ieeexplore . ieee . org / document / 7458129 /](http://ieeexplore.ieee.org/document/7458129/).
- [121] Weeroc, *Triroc 1A*. [Online]. Available: <https://www.weeroc.com/products/sipm-read-out/triroc-1a> (visited on 06/10/2019).